

ةي ل حمل لة قطن م لة ك ب ش ة ي و ض ع ني و ك ت RV ة ل س ل س ل ل ن م ه ج و م ي ل ع (VLAN) ة ي ر ه ا ظ ل ل

ف د ه ل ا

ا ي ق ط ن م ة ل ص ف ن م ة ي ع ر ف ة ك ب ش ي ه (VLAN) ة ي ر ه ا ظ ل ل ة ي ل ح م ل ا ة ق ط ن م ل ا ة ك ب ش
ص ن ا ص خ و ا ة ف ي ط و ب ا ه ب ة ص ا خ ل ل ا ة ي ا ه ن ل ل ط ا ق ن ط ب ت ر ت (IP) ت ن ر ت ن ا ل ل ل و ك و ت و ر ب ل
ة ل ص ف ن م ت ا ك ب ش ا ه ل ن و ك ي ن ا ة ف ل ت خ م ل ا ت ا ر ا د ا ل ل ن ك م م ل ا ن م ل ع ج ي ا ذ ه و . ي ر خ ا ة ك ر ت ش م
د ر ا و م ل ا ي ل ل ل و ص و ل ل ة ي ر ص ح ة ي ن ا ك م ا ا ه ا ض ع ا ل ن و ك ي ت ي ح ب

ن ي ك م ت ل ا ل خ ن م VLAN ت ا ك ب ش ن ي ب د ر ا و م ل ا ة ك ر ا ش م ب ا ض ي ا VLAN ة ك ب ش ح م س ت
ق ح م ه ي د ل ط ا ق ف VLAN ة ك ب ش ا ض ع ا ن ا ل ن ا م ا ل ا ل د ا ع ي ا ذ ه . VLAN ت ا ك ب ش ن ي ب ه ي ج و ت ل ل
ر ي ف و ت ل ل ت ا ل د ع م ا ض ي ا ي ن ع ي ا ذ ه و . ه ذ ه VLAN ة ك ب ش ر ب ع ر م ت ي ت ل ل د ر a و م ل ا ي ل ل ل و ص و ل ل
ل ك ش ب . ط ق ف د ح ا و ز ا ه ج ا ر ش ن ك ل و ة ل ص ف ن م ت ا ك ب ش د و ج و ي ن ع ي VLAN ة ك ب ش ر ش ن ن ا ل
ة ك ب ش و ا ، ة ي ض ا ر ت ف ا VLAN ة ك ب ش ي ل ع RV ة ل س ل س ل ل ن م ت ا ه ج و م ل ا ي و ت ح ت ، ي ض ا ر ت ف ا
up to 6 ت ق ل خ ع ي ط ت س ي ت ن ا . ا ه ر ي ي غ ت و ا ا ه ر ي ر ح ت و ا ا ه ف ذ ح ن ك م ي ا ل ي ت ل ل a و ، VLAN1
ت ي ن ث ت س ا و ا ، untagged ، ت د د ح ت ن ك ع ي ط ت س ي VLANs ل . ك ز ا ه ج ن م ز ا ر ط ل ل ب س ح ، VLANs
ص ا خ ا ن ي م ي ل ل

د ي د خ ت ج ا ح س م RV sery ك ي ل ع ة ي و ض ع VLAN ل ك ش ي ن ا ف ي ك ت ن ا ي د ب ي ن ا ة د ا م ا ذ ه ف د ه ي

ق ي ب ط ت ل ل ة ل ب ا ق ل ل ا ز ه ج ا ل ا

• RV134W و RV132W و RV130W و RV130 و RV110W — RV ة ي ل ل ا

ج م ا ر ب ل ا ر ا د ص ا

- 1.2.0.10 — RV110W
- 1.0.3.16 — RV130، RV130W
- 1.0.0.17 — RV132W
- 1.0.0.21 — RV134W

VLAN ة ي و ض ع ني و ك ت

VLAN تفضأ

هجوم لآ ف بولآ إلآ ءءنءسم لآ ءءاسم لآ ءءالآ إلآ لوءءلآ لآ ءسءب مق 1. ءوطءلآ VLAN ءووضع > LAN > ءكبش لآ رءءآو

فلءءء ءق RV132W هجوم لآ نم ءلآقم لآ هءه ءلآ ءءوءوم لآ روص لآ طآقء لآ مء: ءظءالم زآهء لآ زارط بسء آآءل طصم لآ ءآرآء لآ

Getting Started

Run Setup Wizard

▶ Status and Statistics

▼ Networking

▶ WAN

▼ LAN

LAN Configuration

VLAN Membership

Static DHCP

DHCP Leased Client

DMZ Host

Port Management

▶ Routing

فضة فاضا قوف رقنا 2. ةوطخل

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.
Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged

Add Row Edit Delete

Save Cancel

VLAN تاكبش تافرع م نوكت نأ بجي. لاجم VLAN id لى لى مقرر VLAN تلخد. 3. ةوطخل
VLAN ةكبش فرعمك 40 مادختس متي، لاثملا اذه في. 4094 لى 2 نم قاطنلا في

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.
Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged	Tagged	Tagged

Add Row Edit Delete

Save Cancel

AfterSales لاد متي، لاثملا اذه في. لاجم فصولا في VLAN لى لى فصول تلخد. 4. ةوطخل

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.
Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged ▼	Tagged ▼	Tagged ▼

Add Row Edit Delete

Save Cancel

طفا ح قوف رقنا 5 ةوطخلا

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.
Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged ▼	Tagged ▼	Tagged ▼

Add Row Edit Delete

Save Cancel

رهظتس .ديدخت جاحسم RV sery ك ىل VLAN تفضأ جاجنب ىقلتي نآل تفسو تنأ ةيوضع ةحفص نم يولعل اعزل ايف جاجنب نيوكتل ادادع اظفح مت نيوكت ةلاسر VLAN.

VLAN Membership



Configuration settings have been saved successfully

Create VLANs and assign the Outgoing Frame Type.

Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

VLANs Setting Table

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged	Tagged	Tagged

Add Row

Edit

Delete

Save

Cancel

وضع ةفاضل

ةبسانم ال VLAN ةكبش ل راي تخال ال ةناخ دح، VLAN ةكبش ل اءاضع ا ةفاضل ال 1 ةوطخل ال AfterSales، 40 مقر VLAN ةكبش ل ا ةفاضل ممتس، ل اثل ال اذ ف

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.

Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

VLANs Setting Table

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input checked="" type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged	Tagged	Tagged

Add Row

Edit

Delete

Save

Cancel

ريرحت قوف رقنا 2 ةوطخل ال

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.
Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

VLANs Setting Table

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input checked="" type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged ▼	Tagged ▼	Tagged ▼

Add Row Edit Delete

Save

Cancel

تتكون من VLAN. VLAN تاكيبش نيب هيچوتلا ليطعتل راي تخالالا ةناخ ددح (يراي تخا). 3 ةوطخلال هيچوتلا يف تنمضت نوكل نأ VLANs لىل ناوع نيعي نأ جاتحت تنأ، نوكل inter-VLAN ةينالما.

لطمع وأ ددحم ريغ VLAN تاكيبش نيب هيچوتلا كرت متي، لاثملا اذه يف: ةطخالما.

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.
Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

VLANs Setting Table

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input checked="" type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged ▼	Tagged ▼	Tagged ▼

Add Row Edit Delete

Save

Cancel

رتخأ م ث لدسنملا مهسلا رقنا. لصفملا كءانيم يف ةقاطب VLAN ترتخأ. 4 ةوطخلال دعبتسم وأ، زيميتم تامالع، untagged.

- VLAN لىل نم راطل تلسرأ. VLAN لىل نم وضع untagged نوكل نراقلا — untagged VLAN ءانيملا لىل untagged.
- VLAN لىل نم راطل تلسرأ. VLAN لىل نم زيميتم تامالع وذ وضع نوكل نراقلا — ددح VLAN ءانيملا لىل ددح.
- يضارثفالا دادعإلا وه اذه. VLAN لىل نم وضع سيل ايلاح ءانيملا — تي نثتسا.

VLAN. ةكبش ءاشنإ دنع ذفانملا عيمل

3. ءانيمو، 2. ءانيم، 1. ءانيم نم وضعك AfterSales VLAN لآ تدح، لآثم اذه يف: ةطالام

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.
Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input checked="" type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged	Tagged	Tagged

Add Row Edit Delete

Save Cancel

طفا قوف رقنا 5. ةوطخال

VLAN Membership

Create VLANs and assign the Outgoing Frame Type.
Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input checked="" type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged	Tagged	Tagged

Add Row Edit Delete

Save Cancel

نأب ديكتأ ةلاسرهظتس. ك VLAN لى وضع تفضأ حاجنب ىقلىتي نآلا تفوس تنأ
VLAN. ةيوضع ةحفص نم يولعل اعزلال يف حاجنب اهظفح مت دق نيوكتلا تاداعل

VLAN Membership



Configuration settings have been saved successfully

Create VLANs and assign the Outgoing Frame Type.

Up to five VLANs total can be created. VLAN IDs must be in the range (2 - 4094)

You must save before you can edit or delete.

VLANs Setting Table

Select	VLAN ID	Description	Inter VLAN Routing	Port 1	Port 2	Port 3
<input type="checkbox"/>	1	Default	Disabled	Untagged	Untagged	Untagged
<input type="checkbox"/>	10	Accounting	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	20	Sales	Disabled	Tagged	Tagged	Tagged
<input type="checkbox"/>	30	Shipping	Disabled	Tagged	Tagged	Tagged
<input checked="" type="checkbox"/>	40	AfterSales	<input type="checkbox"/>	Tagged	Tagged	Tagged

Add Row

Edit

Delete

Save

Cancel

VLAN لى لى ناونع تنيع

ليكشت lan>lan ةق قوط 1. ةوطخ لى

Getting Started

Run Setup Wizard

▶ Status and Statistics

▼ Networking

▶ WAN

▼ LAN

LAN Configuration

VLAN Membership

Static DHCP

DHCP Leased Client

DMZ Host

Port Management

مزلي يتالي VLAN ةكبش رتخاو VLAN ةكبش ل ل دس ن م ل م ه س ل ا ق و ف ر ق ن ا 2. ة و ط خ ل ا IP. ن ا و ن ع م ا د خ ت س ا ب ا ه ن ي ي ع ت

40 م ق ر VLAN ةكبش ل ا IP ن ا و ن ع ة ف ا ض ا ب م و ق ن س ، ل ا ث م ل ا ا ذ ه ي ف : ة ط ح ا ل م

LAN Configuration

Network

Host Name:

Domain Name:

IPv4

VLAN:

Local IP Address: (Hint: 192.168.1.1)

Subnet Mask:

Server Settings(DHCP)

VLAN. ن ا ل ن ي ع ي ن ا ج ا ت ح ت ت ن ا ن ا و ن ع ل ا ، ل ا ج م ي ل ح م ن ا و ن ع ل ا ت ح ت ت ل خ د 3. ة و ط خ ل ا

40 م ق ر VLAN ةكبش ل ا IP 192.168.40.1 ن ا و ن ع ن ي ي ع ت ب م و ق ن ، ل ا ث م ل ا ا ذ ه ي ف : ة ط ح ا ل م

LAN Configuration

Network

Host Name:

Domain Name:

IPv4

VLAN:

Local IP Address: (Hint: 192 168 1 1)

Subnet Mask:

ة ي ع ر ف ل ا ةكبش ل ا ع ا ن ق ل ق ح ي ف VLAN ةكبش ل ا ة ي ع ر ف ل ا ةكبش ل ا ع ا ن ق ل خ د ا 4. ة و ط خ ل ا

LAN Configuration

Network

Host Name:

RV134W

Domain Name:

IPv4

VLAN:

40

Local IP Address:

192

168

40

1

(Hint: 192 168 1 1)

Subnet Mask:

255

255

255

0

ظفح قوف رقنا 5 ةوطخ لآ

DHCP Option 66/150 & 67:

Enable

TFTP Server Host Name:

TFTP Server IP:

Configuration Filename:

Save

Cancel

VLAN لآ لآ ناووع تنيع حاجنب نآلآ تفوس تنأ

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةللخت. فرتمة مچرت مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او
ىل إأمءءاد ءوچرلاب ةصوء و تامةرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةل صأل ةل ءل ءن إل دن تسمل