



Release Notes for the Cisco Secure Firewall ASA Series, 9.18(x)

First Published: 2022-06-06

Last Modified: 2024-05-22

Release Notes for the Secure Firewall ASA Series, 9.18(x)

This document contains release information for ASA software Version 9.18.

Important Notes

- **ASDM signed-image support in 9.18(2)/7.18(1.152) and later**—The ASA now validates whether the ASDM image is a Cisco digitally signed image. If you try to run an older ASDM image with an ASA version with this fix, ASDM will be blocked and the message “%ERROR: Signature not valid for file disk0:./<filename>” will be displayed at the ASA CLI. ASDM release 7.18(1.152) and later are backwards compatible with all ASA versions, even those without this fix. ([CSCwb05291](#), [CSCwb05264](#))
- **Downgrade issue from 9.18 or later**—There is a behavior change in 9.18 where the **access-group** command will be listed before its **access-list** commands. If you downgrade, the **access-group** command will be rejected because it has not yet loaded the **access-list** commands. This outcome occurs even if you had previously enabled the **forward-reference enable** command, because that command is now removed. Before you downgrade, be sure to copy all **access-group** commands manually, and then after downgrading, re-enter them.
- **9.18(1) upgrade issue if you enabled HTTPS/ASDM (with HTTPS authentication) and SSL on the same interface with the same port**—If you enable both SSL (**webvpn > enable interface**) and HTTPS/ASDM (**http**) access on the same interface, you can access AnyConnect from **https://ip_address** and ASDM from **https://ip_address/admin**, both on port 443. However, if you also enable HTTPS authentication (**aaa authentication http console**), then you must specify a different port for ASDM access starting in 9.18(1). Make sure you change the port before you upgrade using the **http** command. ([CSCvz92016](#))
- **Behavior change for Secure Firewall 3100 in 9.18(2.7)**—When you set the FEC to Auto using the **fec** command on the Secure Firewall 3100 fixed ports, the default type is now set to cl108-rs instead of cl74-fc for 25 GB SR, CSR, and LR transceivers. ([CSCwc75082](#))

System Requirements

ASDM requires a computer with a CPU with at least 4 cores. Fewer cores can result in high memory usage.

ASA and ASDM Compatibility

For information about ASA/ASDM software and hardware requirements and compatibility, including module compatibility, see [Cisco Secure Firewall ASA Compatibility](#).

VPN Compatibility

For VPN compatibility, see [Supported VPN Platforms, Cisco ASA 5500 Series](#).

New Features

This section lists new features for each release.



Note New, changed, and deprecated syslog messages are listed in the syslog message guide.

New Features in ASA 9.18(4)

Released: October 3, 2023

Feature	Description
High Availability and Scalability Features	
Reduced false failovers for ASA high availability	We now introduced an additional heartbeat module in the data plane of the ASA high availability. This heartbeat module helps to avoid false failovers or split-brain scenarios that can happen due to traffic congestion in the control plain or CPU overload. <i>Also in 9.20(1).</i>
show failover statistics includes client statistics	The failover client packet statistics are now enhanced to improve debuggability. The show failover statistics command is enhanced to display np-clients (data-path clients) and cp-clients (control-plane clients) information. Modified commands: show failover statistics cp-clients , show failover statistics dp-clients <i>Also in 9.20(2).</i>
show failover statistics events includes new events	The show failover statistics events command is now enhanced to identify the local failures notified by the App agent: failover link uptime, supervisor heartbeat failures, and disk full issues. Modified commands: show failover statistics events <i>Also in 9.20(2).</i>
Interface Features	

Feature	Description
FXOS local-mgmt show command improvements	<p>See the following additions for interface show commands in FXOS local-mgmt:</p> <ul style="list-style-type: none"> • Added the show portmanager switch tail-drop-allocated buffers all command • Include Ethernet port ID in show portmanager switch status command • For the Secure Firewall 3100, added the show portmanager switch default-rule-drop-counter command <p>New/Modified FXOS commands: show portmanager switch tail-drop-allocated buffers all, show portmanager switch status, show portmanager switch default-rule-drop-counter</p>
Administrative, Monitoring, and Troubleshooting Features	
show tech support improvements	<p>Added output to show tech support for:</p> <ul style="list-style-type: none"> • show storage detail, show slot expand detail for the Secure Firewall 3100 in show tech support brief • Recent messages from dpdk.log in the flash for the ASA Virtual • Control link state for the Firepower 1010 • show failover statistics • FXOS local-mgmt show portmanager switch tail-drop-allocated buffers all • show controller • DPDK mbuf pool statistics <p>New/Modified commands: show tech support</p>

New Features in ASA 9.18(3)

Released: February 16, 2023

Feature	Description
Platform Features	
Firepower 1010E	<p>We introduced the Firepower 1010E. This model is the same as the Firepower 1010 except it doesn't have Power Over Ethernet ports.</p> <p>ASDM support in 7.19(1.90) or 7.18(2.1). ASDM 7.19(1) does not support this model. <i>Also in 9.18(2.218). This model is not supported in 9.19(1).</i></p>
Interface Features	

New Features in ASA 9.18(2)

Feature	Description
Default Forward Error Correction (FEC) on Secure Firewall 3100 fixed ports changed to cl108-rs from cl74-fc for 25 GB+ SR, CSR, and LR transceivers	When you set the FEC to Auto on the Secure Firewall 3100 fixed ports, the default type is now set to cl108-rs instead of cl74-fc for 25 GB SR, CSR, and LR transceivers. New/Modified commands: fec <i>Also in 9.19(1) and 9.18(2.7).</i>
VPN Features	
AnyConnect connection authentication using SAML	In a DNS load balancing cluster, when SAML authentication is configured on ASAs, you can specify a local base URL that uniquely resolves to the device on which the configuration is applied. New/Modified commands: local-base-urlurl

New Features in ASA 9.18(2)

Released: August 10, 2022

Feature	Description
Interface Features	
Loopback interface support for BGP and management traffic	You can now add a loopback interface and use it for the following features: <ul style="list-style-type: none"> • AAA • BGP • SNMP • SSH • Syslog • Telnet New/Modified commands: interface loopback, logging host, neighbor update-source, snmp-server host, ssh, telnet
ping command changes	To support pinging a loopback interface, the ping command now has changed behavior. If you specify the interface in the command, the source IP address matches the specified interface IP address, but the actual egress interface is determined by a route lookup using the data routing table. New/Modified commands: ping

New Features in ASA 9.18(1)

Released: June 6, 2022

Feature	Description
Platform Features	
ASAv-AWS Security center integration for AWS GuardDuty	You can now integrate Amazon GuardDuty service with ASAv. The integration solution helps you to capture and process the threat analysis data or results (malicious IP addresses) reported by Amazon GuardDuty. You can configure and feed these malicious IP addresses in the ASAv to protect the underlying networks and applications.
Firewall Features	
Forward referencing of ACLs and objects is always enabled. In addition, object group search for access control is now enabled by default.	<p>You can refer to ACLs or network objects that do not yet exist when configuring access groups or access rules.</p> <p>In addition, object group search is now enabled by default for access control for <i>new</i> deployments. Upgrading devices will continue to have this command disabled. If you want to enable it (recommended), you must do so manually.</p> <p>Caution If you downgrade, the access-group command will be rejected because it has not yet loaded the access-list commands. This outcome occurs even if you had previously enabled the forward-reference enable command, because that command is now removed. Before you downgrade, be sure to copy all access-group commands manually, and then after downgrading, re-enter them.</p> <p>We removed the forward-reference enable command and changed the default for new deployments for object-group-search access-control to enabled.</p>
Routing Features	
Path monitoring metrics in PBR.	<p>PBR uses the metrics to determine the best path (egress interface) for forwarding the traffic. Path monitoring periodically notifies PBR with the monitored interface whose metric got changed. PBR retrieves the latest metric values for the monitored interfaces from the path monitoring database and updates the data path.</p> <p>New/Modified commands: clear path-monitoring, policy-route, show path-monitoring</p>
Interface Features	
Pause Frames for Flow Control for the Secure Firewall 3100	<p>If you have a traffic burst, dropped packets can occur if the burst exceeds the buffering capacity of the FIFO buffer on the NIC and the receive ring buffers. Enabling pause frames for flow control can alleviate this issue.</p> <p>New/Modified commands: flowcontrol send on</p>
Breakout ports for the Secure Firewall 3130 and 3140	<p>You can now configure four 10GB breakout ports for each 40GB interface on the Secure Firewall 3130 and 3140.</p> <p>New/Modified commands: breakout</p>
License Features	

Feature	Description
Secure Firewall 3100 support for the Carrier license	The Carrier license enables Diameter, GTP/GPRS, SCTP inspection. New/Modified commands: feature carrier
Certificate Features	
Mutual LDAPS authentication.	You can configure a client certificate for the ASA to present to the LDAP server when it requests a certificate to authenticate. This feature applies when using LDAP over SSL. If an LDAP server is configured to require a peer certificate, the secure LDAP session will not complete and authentication/authorization requests will fail. New/Modified commands: ssl-client-certificate .
Authentication: Validate certificate name or SAN	When a feature specific reference-identity is configured, the peer certificate identity is validated with the matching criteria specified under crypto ca reference-identity <name> submode commands. If there is no match found in the peer certificate Subject Name/SAN or if the FQDN specified with reference-identity submode command fail to resolve, the connection is terminated The reference-identity CLI is configured as a submode command for aaa-server host configuration and ddns configuration. New/Modified commands: ldap-over-ssl , ddns update method , and show update method .
Administrative, Monitoring, and Troubleshooting Features	
Multiple DNS server groups	You can now use multiple DNS server groups: one group is the default, while other groups can be associated with specific domains. A DNS request that matches a domain associated with a DNS server group will use that group. For example, if you want traffic destined to inside eng.cisco.com servers to use an inside DNS server, you can map eng.cisco.com to an inside DNS group. All DNS requests that do not match a domain mapping will use the default DNS server group, which has no associated domains. For example, the DefaultDNS group can include a public DNS server available on the outside interface. New/Modified commands: dns-group-map , dns-to-domain
Dynamic Logging Rate-limit	A new option to limit logging rate when block usage exceeds a specified threshold value was added. It dynamically limits the logging rate as the rate limiting is disabled when the block usage returns to normal value. New/Modified commands: logging rate-limit
Packet Capture for Secure Firewall 3100 devices	The provision to capture switch packets was added. This option can be enabled only for Secure Firewall 3100 devices. New/Modified commands: capture real-time
VPN Features	

Feature	Description
IPsec flow offload.	<p>On the Secure Firewall 3100, IPsec flows are offloaded by default. After the initial setup of an IPsec site-to-site VPN or remote access VPN security association (SA), IPsec connections are offloaded to the field-programmable gate array (FPGA) in the device, which should improve device performance.</p> <p>New/Modified commands: clear flow-offload-ipsec, flow-offload-ipsec, show flow-offload-ipsec</p>
Certificate and SAML for Authentication	<p>You can configure remote access VPN connection profiles for certificate and SAML authentication. Users can configure VPN settings to authenticate a machine certificate or user certificate before a SAML authentication/authorization is initiated. This can be done using DAP certificate attributes along with user specific SAML DAP attributes.</p> <p>New/Modified commands: authentication saml certificate, authentication certificate saml, authentication multiple-certificate saml</p>

Upgrade the Software

This section provides the upgrade path information and a link to complete your upgrade.

Upgrade Link

To complete your upgrade, see the [ASA upgrade guide](#).

Upgrade Path: ASA Appliances

To view your current version and model, use one of the following methods:

- ASDM: Choose **Home > Device Dashboard > Device Information**.
- CLI: Use the **show version** command.

This table provides upgrade paths for ASA. Some older versions require an intermediate upgrade before you can upgrade to a newer version. Recommended versions are in **bold**.

Be sure to check the upgrade guidelines for each release between your starting version and your ending version. You may need to change your configuration before upgrading in some cases, or else you could experience an outage.

For guidance on security issues on the ASA, and which releases contain fixes for each issue, see the [ASA Security Advisories](#).



-
- Note** ASA 9.16 was the final version for the ASA 5506-X, 5508-X, and 5516-X.
 ASA 9.14 was the final version for the ASA 5525-X, 5545-X, and 5555-X.
 ASA 9.12 was the final version for the ASA 5512-X, 5515-X, 5585-X, and ASASM.
 ASA 9.2 was the final version for the ASA 5505.
 ASA 9.1 was the final version for the ASA 5510, 5520, 5540, 5550, and 5580.
-

Table 1: Upgrade Path

Current Version	Interim Upgrade Version	Target Version
9.17	—	Any of the following: → 9.18
9.16	—	Any of the following: → 9.18 → 9.17
9.15	—	Any of the following: → 9.18 → 9.17 → 9.16
9.14	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15
9.13	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14

Current Version	Interim Upgrade Version	Target Version
9.12	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14
9.10	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12
9.9	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12
9.8	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12

Current Version	Interim Upgrade Version	Target Version
9.7	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12 → 9.8
9.6	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12 → 9.8
9.5	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12 → 9.8

Current Version	Interim Upgrade Version	Target Version
9.4	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12 → 9.8
9.3	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12 → 9.8
9.2	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14 → 9.12 → 9.8
9.1(2), 9.1(3), 9.1(4), 9.1(5), 9.1(6), or 9.1(7.4)	—	Any of the following: → 9.14 → 9.12 → 9.8 → 9.1(7.4)

Current Version	Interim Upgrade Version	Target Version
9.1(1)	→ 9.1(2)	Any of the following: → 9.14 → 9.12 → 9.8 → 9.1(7.4)
9.0(2), 9.0(3), or 9.0(4)	—	Any of the following: → 9.14 → 9.12 → 9.8 → 9.6 → 9.1(7.4)
9.0(1)	→ 9.0(4)	Any of the following: → 9.14 → 9.12 → 9.8 → 9.1(7.4)
8.6(1)	→ 9.0(4)	Any of the following: → 9.14 → 9.12 → 9.8 → 9.1(7.4)
8.5(1)	→ 9.0(4)	Any of the following: → 9.12 → 9.8 → 9.1(7.4)
8.4(5+)	—	Any of the following: → 9.12 → 9.8 → 9.1(7.4) → 9.0(4)

Current Version	Interim Upgrade Version	Target Version
8.4(1) through 8.4(4)	→ 9.0(4)	→ 9.12 → 9.8 → 9.1(7.4)
8.3	→ 9.0(4)	Any of the following: → 9.12 → 9.8 → 9.1(7.4)
8.2 and earlier	→ 9.0(4)	Any of the following: → 9.12 → 9.8 → 9.1(7.4)

Upgrade Path: ASA on Firepower 2100 in Platform Mode

To view your current version and model, use one of the following methods:

- ASDM: Choose **Home > Device Dashboard > Device Information**.
- CLI: Use the **show version** command.

This table provides upgrade paths for the ASA on the Firepower 2100 in Platform mode. Some versions require an intermediate upgrade before you can upgrade to a newer version. Recommended versions are in **bold**.

Be sure to check the upgrade guidelines for each release between your starting version and your ending version. You may need to change your configuration before upgrading in some cases, or else you could experience an outage.

For guidance on security issues on the ASA, and which releases contain fixes for each issue, see the [ASA Security Advisories](#).

Table 2: Upgrade Path

Current Version	Interim Upgrade Version	Target Version
9.17	—	Any of the following: → 9.18
9.16	—	Any of the following: → 9.18 → 9.17

Current Version	Interim Upgrade Version	Target Version
9.15	—	Any of the following: → 9.18 → 9.17 → 9.16
9.14	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15
9.13	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14
9.12	—	Any of the following: → 9.18 → 9.17 → 9.16 → 9.15 → 9.14
9.10	→ 9.17	Any of the following: → 9.18
9.10	—	Any of the following: → 9.17 → 9.16 → 9.15 → 9.14 → 9.12

Current Version	Interim Upgrade Version	Target Version
9.9	→ 9.17	Any of the following: → 9.18
9.9	—	Any of the following: → 9.17 → 9.16 → 9.15 → 9.14 → 9.12
9.8	→ 9.17	Any of the following: → 9.18
9.8	—	Any of the following: → 9.17 → 9.16 → 9.15 → 9.14 → 9.12

Upgrade Path: ASA Logical Devices for the Firepower 4100/9300

For upgrading, see the following guidelines:

- FXOS—For 2.2.2 and later, you can upgrade directly to a higher version. When upgrading from versions earlier than 2.2.2, you need to upgrade to each intermediate version. Note that you cannot upgrade FXOS to a version that does not support your current logical device version. You will need to upgrade in steps: upgrade FXOS to the highest version that supports your current logical device; then upgrade your logical device to the highest version supported with that FXOS version. For example, if you want to upgrade from FXOS 2.2/ASA 9.8 to FXOS 2.13/ASA 9.19, you would have to perform the following upgrades:
 1. FXOS 2.2→FXOS 2.11 (the highest version that supports 9.8)
 2. ASA 9.8→ASA 9.17 (the highest version supported by 2.11)
 3. FXOS 2.11→FXOS 2.13
 4. ASA 9.17→ASA 9.19
- ASA—ASA lets you upgrade directly from your current version to any higher version, noting the FXOS requirements above.

Table 3: ASA or Threat Defense, and Firepower 4100/9300 Compatibility

FXOS Version	Model	ASA Version	Threat Defense Version
2.14(1)	Firepower 4112	9.18	7.4 (recommended)
		9.17	7.3
		9.16	7.2
		9.15	7.1
		9.14	7.0
			6.7
			6.6
	Firepower 4145 Firepower 4125 Firepower 4115 Firepower 9300 SM-56 Firepower 9300 SM-48 Firepower 9300 SM-40	9.18	7.4 (recommended)
		9.17	7.3
		9.16	7.2
		9.15	7.1
		9.14	7.0
			6.7
			6.6
2.13	Firepower 4112	9.18	7.3 (recommended)
		9.17	7.2
		9.16	7.1
		9.15	7.0
		9.14	6.7
			6.6
	Firepower 4145 Firepower 4125 Firepower 4115 Firepower 9300 SM-56 Firepower 9300 SM-48 Firepower 9300 SM-40	9.18	7.3 (recommended)
		9.17	7.2
		9.16	7.1
		9.15	7.0
		9.14	6.7
			6.6

FXOS Version	Model	ASA Version	Threat Defense Version
2.12	Firepower 4112	9.18 (recommended) 9.17 9.16 9.15 9.14	7.2 (recommended) 7.1 7.0 6.7 6.6
	Firepower 4145	9.18 (recommended) 9.17 9.16 9.15 9.14 9.12	7.2 (recommended) 7.1 7.0 6.7 6.6 6.4
	Firepower 4125		
	Firepower 4115		
	Firepower 9300 SM-56		
	Firepower 9300 SM-48		
	Firepower 9300 SM-40		
	Firepower 4150	9.18 (recommended) 9.17 9.16 9.15 9.14 9.12	7.2 (recommended) 7.1 7.0 6.7 6.6 6.4
	Firepower 4140		
	Firepower 4120		
	Firepower 4110		
	Firepower 9300 SM-44		
	Firepower 9300 SM-36		
	Firepower 9300 SM-24		

FXOS Version	Model	ASA Version	Threat Defense Version
2.11	Firepower 4112	9.17 (recommended)	7.1 (recommended)
		9.16	7.0
		9.15	6.7
		9.14	6.6
	Firepower 4145 Firepower 4125 Firepower 4115	9.17 (recommended)	7.1 (recommended)
		9.16	7.0
		9.15	6.7
		9.14	6.6
		9.12	6.4
		9.12	6.4
	Firepower 9300 SM-56 Firepower 9300 SM-48 Firepower 9300 SM-40	9.17 (recommended)	7.1 (recommended)
		9.16	7.0
		9.15	6.7
		9.14	6.6
		9.12	6.4
		9.12	6.4
		9.8	6.4
		9.8	6.4
	Firepower 4150 Firepower 4140 Firepower 4120 Firepower 4110	9.17 (recommended)	7.1 (recommended)
9.16		7.0	
9.15		6.7	
9.14		6.6	
9.12		6.4	
9.8		6.4	
9.8		6.4	
Firepower 9300 SM-44 Firepower 9300 SM-36 Firepower 9300 SM-24	9.17 (recommended)	7.1 (recommended)	
	9.16	7.0	
	9.15	6.7	

FXOS Version	Model	ASA Version	Threat Defense Version
2.10 Note For compatibility with 7.0.2+ and 9.16(3.11)+, you need FXOS 2.10(1.179)+.	Firepower 4112	9.16 (recommended) 9.15 9.14	7.0 (recommended) 6.7 6.6
	Firepower 4145 Firepower 4125 Firepower 4115	9.16 (recommended) 9.15 9.14	7.0 (recommended) 6.7 6.6
	Firepower 9300 SM-56 Firepower 9300 SM-48 Firepower 9300 SM-40	9.12	6.4
	Firepower 4150 Firepower 4140 Firepower 4120 Firepower 4110	9.16 (recommended) 9.15 9.14 9.12	7.0 (recommended) 6.7 6.6 6.4
	Firepower 9300 SM-44 Firepower 9300 SM-36 Firepower 9300 SM-24	9.8	
	Firepower 4112	9.15 (recommended) 9.14	6.7 (recommended) 6.6
	Firepower 4145 Firepower 4125 Firepower 4115	9.15 (recommended) 9.14 9.12	6.7 (recommended) 6.6 6.4
	Firepower 9300 SM-56 Firepower 9300 SM-48 Firepower 9300 SM-40		
	Firepower 4150 Firepower 4140 Firepower 4120 Firepower 4110	9.15 (recommended) 9.14 9.12 9.8	6.7 (recommended) 6.6 6.4
	Firepower 9300 SM-44 Firepower 9300 SM-36 Firepower 9300 SM-24		

FXOS Version	Model	ASA Version	Threat Defense Version
2.8	Firepower 4112	9.14	6.6 Note 6.6.1+ requires FXOS 2.8(1.125)+.
	Firepower 4145	9.14 (recommended) 9.12 Note Firepower 9300 SM-56 requires ASA 9.12(2)+	6.6 (recommended) Note 6.6.1+ requires FXOS 2.8(1.125)+. 6.4
	Firepower 4125		
	Firepower 4115		
	Firepower 9300 SM-56	9.14 (recommended) 9.12 9.8	6.6 (recommended) Note 6.6.1+ requires FXOS 2.8(1.125)+. 6.4 6.2.3
	Firepower 9300 SM-48		
	Firepower 9300 SM-40		
	Firepower 4150		
	Firepower 4140	9.12 Note Firepower 9300 SM-56 requires ASA 9.12.2+	6.4
	Firepower 4120		
Firepower 4110			
Firepower 9300 SM-44			
Firepower 9300 SM-36			
Firepower 9300 SM-24			
2.6(1.157) Note You can now run ASA 9.12+ and FTD 6.4+ on separate modules in the same Firepower 9300 chassis	Firepower 4145	9.12 Note Firepower 9300 SM-56 requires ASA 9.12.2+	6.4
	Firepower 4125		
	Firepower 4115		
	Firepower 9300 SM-56	9.12 (recommended) 9.8	6.4 (recommended) 6.2.3
	Firepower 9300 SM-48		
	Firepower 9300 SM-40		
	Firepower 4150		
	Firepower 4140	9.12 Note Firepower 9300 SM-56 requires ASA 9.12.2+	6.4
	Firepower 4120		
	Firepower 4110		
Firepower 9300 SM-44			
Firepower 9300 SM-36			
Firepower 9300 SM-24			

FXOS Version	Model	ASA Version	Threat Defense Version
2.6(1.131)	Firepower 9300 SM-48 Firepower 9300 SM-40	9.12	Not supported
	Firepower 4150 Firepower 4140 Firepower 4120 Firepower 4110	9.12 (recommended) 9.8	
	Firepower 9300 SM-44 Firepower 9300 SM-36 Firepower 9300 SM-24		
2.3(1.73)	Firepower 4150 Firepower 4140 Firepower 4120 Firepower 4110	9.8 Note 9.8(2.12)+ is required for flow offload when running FXOS 2.3(1.130)+.	6.2.3 (recommended) Note 6.2.3.16+ requires FXOS 2.3.1.157+
	Firepower 9300 SM-44 Firepower 9300 SM-36 Firepower 9300 SM-24		
2.3(1.66) 2.3(1.58)	Firepower 4150 Firepower 4140 Firepower 4120 Firepower 4110	9.8 Note 9.8(2.12)+ is required for flow offload when running FXOS 2.3(1.130)+.	
	Firepower 9300 SM-44 Firepower 9300 SM-36 Firepower 9300 SM-24		
2.2	Firepower 4150 Firepower 4140 Firepower 4120 Firepower 4110	9.8	Threat Defense versions are EoL
	Firepower 9300 SM-44 Firepower 9300 SM-36 Firepower 9300 SM-24		

Note on Downgrades

Downgrade of FXOS images is not officially supported. The only Cisco-supported method of downgrading an image version of FXOS is to perform a complete re-image of the device.

Open and Resolved Bugs

The open and resolved bugs for this release are accessible through the Cisco Bug Search Tool. This web-based tool provides you with access to the Cisco bug tracking system, which maintains information about bugs and vulnerabilities in this product and other Cisco hardware and software products.



Note You must have a Cisco.com account to log in and access the Cisco Bug Search Tool. If you do not have one, you can [register for an account](#). If you do not have a Cisco support contract, you can only look up bugs by ID; you cannot run searches.

For more information about the Cisco Bug Search Tool, see the [Bug Search Tool Help & FAQ](#).

Open Bugs in Version 9.18(x)

The following table lists select open bugs at the time of this Release Note publication.

Identifier	Headline
CSCwe47689	FXOS should provide an option to tag and display counters for selected flows/packets
CSCwe68349	ACP deploy failed on KP-HA
CSCwe98264	Snort3 crash in KP driver code in 7.2.4-114
CSCwf18926	ASAv VMware traceback and reload with Thread Name: PTHREAD-1549
CSCwf63480	Umbrella registration succeeds after cert validation failure
CSCwf65710	Current connection count is negative on 'show service policy' - conn limit exceeded
CSCwh36906	FTD traceback with Thread Name: PIM IPv4
CSCwh43230	Strong Encryption license is not getting applied to ASA firewalls in HA.
CSCwh47053	ASA/FTD may traceback and reload in Thread Name 'dns_cache_timer'
CSCwh58090	FP4110 crashing on asa code 9.18(3)53 with no direct cause
CSCwh58467	ASA does not sent 'warmstart' snmp trap
CSCwh60504	WM: Lina crash at dispatch_lb_poll_worker with invalid opcode(sig 4)
CSCwh65128	LINA show tech-support fails to generate as part of sf_troubleshoot.pl (Troubleshoot file)
CSCwh66359	ASDM can not see log timestamp after enable logging timestamp on cli

Identifier	Headline
CSCwh68482	ASA/FTD: Traceback in Process Name: lina
CSCwh68964	FTD FP2100: LDAP External authentication may fail for username containing backslash "\"
CSCwh69346	ASA: Traceback and reload when restore configuration using CLI
CSCwh69585	Cruz Adapter down in one of the modules
CSCwh69843	ASA in transparent mode doesn't send equal IPv6 Router Advertisement packets to all nodes
CSCwh71050	FXOS : Duplication of NTP entry results in Error message : Unreachable Or Invalid Ntp Server
CSCwh71161	ASA FTD: Traceback & reload in thread Name: update_mem_reference
CSCwh71314	ASA/FTD: Traceback due to wrong calc leading to negative transfer bytes passed to memcpy function
CSCwh76458	ASA/FTD drops multicast traffic when there is no mroute entry when using Bidir PIM.
CSCwh77348	ASA: Traceback and reload when executing the command "show nat pool detail" on a cluster setup
CSCwh78691	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwh80716	Interface connected with PPPoE may go down unexpectedly

Resolved Bugs

This section lists resolved bugs per release.

Resolved Bugs in Version 9.18(4)

The following table lists select resolved bugs at the time of this Release Note publication.

Identifier	Headline
CSCvt25221	FTD traceback in Thread Name cli_xml_server when deploying QoS policy
CSCvu24703	FTD - Flow-Offload should be able to coexist with Rate-limiting Feature (QoS)
CSCvx04003	Lack of throttling of ARP miss indications to CP leads to oversubscription
CSCvx71936	FXOS: Fault "The password encryption key has not been set." displayed on FPR1000 and FPR2100 devices
CSCwa89116	Clean up session index handling in IKEv2/SNMP/Session-mgr for MIB usage
CSCwa93215	Primary node disconnected from VPN-Cluster when performed HA failover on Primary with DNS lookup

Identifier	Headline
CSCwa96920	ASA/FTD may traceback and reload in process Lina
CSCwb24306	duplicate log entry for /mnt/disk0/log/asa_snmp.log
CSCwb44848	ASA/FTD Traceback and reload in Process Name: lina
CSCwb66382	ASAv - 9344 Block not created automatically after enabling JumboFrames, breaks OSPF MD5
CSCwb94431	MFIB RPF failed counter instead of Other drops increments when outgoing interface list is Null
CSCwb95453	ASA: The timestamp for all logs generated by Admin context are the same
CSCwc49180	Statsclient hap reset and boot loop after enabling SNMP unification in 92.13
CSCwc49655	FTPS getting ssl3_get_record:bad record type during connection for KK and DR rules
CSCwc67031	vti hub with NAT-T enabled pinholes connections are looping and causing snort busy drops
CSCwc82205	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwc87963	ASAv "Unable to retrieve license info. Please try again later"
CSCwc89924	FXOS ASA/FTD SNMP OID to poll Internal-data 'no buffer' interface counters
CSCwd02864	logging/syslog is impacted by SNMP traps and logging history
CSCwd04210	ASA: ASDM sessions stuck in CLOSE_WAIT causing lack of MGMT
CSCwd07278	ASA/FTD tmatch compilation check when unit joins the cluster, when TCM is off
CSCwd09870	AnyConnect SAML using external browser and round robin DNS intermittently fails
CSCwd10822	Failover trigger due to Inspection engine in other unit has failed due to disk failure
CSCwd10880	critical health alerts 'user configuration(FSM.sam.dme.AaaUserEpUpdateUserEp)' on 2100/3100 devices
CSCwd16906	ASA/FTD may traceback and reload in Thread Name 'lina' following policy deployment
CSCwd22413	EIGRPv6 - Crashed with "mem_lock: Assertion mem_refcount' failed" on LINA.
CSCwd23188	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwd30856	User with no vpn-filter may get additional access when per-user-override is set
CSCwd33054	DHCP Relay is looping back the DHCP offer packet causing dhcprelay to fail on the FTD/ASA
CSCwd34288	FP1000 - During boot process in LINA mode, broadcasts leaked between interfaces resulting in storm

Identifier	Headline
CSCwd37135	ASA/FTD traceback and reload on thread name fover_fail_check
CSCwd38583	ASA/FTD: Command "no snmp-server enable oid mempool" enabled by default or enforced during upgrades
CSCwd43666	Analyze why there is no logrotate for /opt/cisco/config/var/log/ASAconsole.log
CSCwd46741	fxos log rotate failing to cycle files, resulting in large file sizes
CSCwd46780	ASA/FTD: Traceback and reload in Thread Name: appAgent_reply_processor_thread
CSCwd53635	AWS: SSL decryption failing with Geneve tunnel interface
CSCwd56296	FTD Lina traceback and reload in Thread Name 'IP Init Thread'
CSCwd58188	Inline-pair's state could not able to auto recover from hardware-bypass to standby mode.
CSCwd58528	Memory depletion while running EMIX traffic profile on QP HA active node
CSCwd59736	ASA/FTD: Traceback and reload due to SNMP group configuration during upgrade
CSCwd62138	ASA Connections stuck in idle state when DCD is enabled
CSCwd63961	AC clients fail to match DAP rules due to attribute value too large
CSCwd66815	Lina changes to support - Snort3 traceback in daq-pdts while handling FQDN based traffic
CSCwd67101	FPR1150 : Exec format error seen and the device hung until reload when erase secure all is executed
CSCwd68088	ASA FTD: Implement different TLS diffie-hellman prime based on RFC recommendation
CSCwd68346	ASA MIO-blade heartbeat failure due to kernel crash, leads to MEZZ core
CSCwd68745	QEMU KVM console got stuck in "Booting the kernel" page
CSCwd69454	Port-channel interfaces of secondary unit are in waiting status after reload
CSCwd71254	ASA/FTD may traceback and reload in idfw fqdn hash lookup
CSCwd72680	FXOS: FP2100 FTW timeout triggered by high CPU usage during FTD Access Control Policy deploy.
CSCwd74839	30+ seconds data loss when unit re-join cluster
CSCwd78624	ASA configured with HA may traceback and reload with multiple input/output error messages
CSCwd80343	MI FTD running 7.0.4 is on High disk utilization
CSCwd81123	High CPU Utilization on FXOS for processes smConlogger

Identifier	Headline
CSCwd81538	FTD Traffic failure due to 9344 block depletion in peer_proxy_tx_q
CSCwd82235	LINA Traceback on FPR-1010 under Thread Name: update_cpu_usage
CSCwd84046	Microsoft SCEP enrollment fails to get ASA identity cert - Unable to verify PKCS7
CSCwd84133	ASA/FTD may traceback and reload in Thread Name 'telnet/ci'
CSCwd84153	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwd84868	Observing some devcmd failures and checkheaps traceback when flow offload is not used.
CSCwd85927	Traceback and reload when webvpn users match DAP access-list with 36k elements
CSCwd86535	ASA/FTD: Traceback and Reload on Netflow timer infra
CSCwd86929	Cut-Through Proxy does not work with HTTPS traffic
CSCwd87438	Enhance logging mechanism for syslogs
CSCwd88585	ASA/FTD NAT Pool Cluster allocation and reservation discrepancy between units
CSCwd89095	Stratix5950 and ISA3000 LACP channel member SFP port suspended after reload
CSCwd89848	ASA/FTD failure due to heartbeat loss between chassis and blade
CSCwd91421	ASA/FTD may traceback and reload in logging_cfg processing
CSCwd92804	FAN LED flashing amber on FPR2100
CSCwd93376	Clientless VPN users are unable to download large files through the WebVPN portal
CSCwd94096	Anyconnect users unable to connect when ASA using different authentication and authorization server
CSCwd94183	Blade not coming up after FXOS update support on multi-instance due to ssp_ntp.log log rotation prob
CSCwd95436	Primary ASA traceback upon rebooting the secondary
CSCwd95908	ASA/FTD traceback and reload, Thread Name: rtcli async executor process
CSCwd96493	Link Up seen for a few seconds on FPR1010 during bootup
CSCwd96500	FTD: Unable to configure WebVPN Keepout or Certificate Map on FPR3100
CSCwd96755	ASA is unexpected reload when doing backup
CSCwd96766	41xx: Blade does not capture or log a reboot signal
CSCwd97020	ASA/FTD: External IDP SAML authentication fails with Bad Request message
CSCwe00864	License Commands go missing in Cluster data unit if the Cluster join fails.

Identifier	Headline
CSCwe03529	FTD traceback and reload while deploying PAT POOL
CSCwe03631	Need to provide rate-limit on "logging history & mode;"
CSCwe03991	FTD/ASA traceback and reload during tmatch compilation process
CSCwe05913	FTD traceback/reloads - Icmp error packet processing involves snp_nat_xlate_identity
CSCwe06562	FPR1K/FPR2K: Increase in failover time in Transparent Mode with high number of Sub-Interfaces
CSCwe07722	Cluster data unit drops non-VPN traffic with ASP reason "VPN reclassify failure
CSCwe08729	FPR1120:connections are getting teardown after switchover in HA
CSCwe09074	None option under trustpoint doesn't work when CRL check is failing
CSCwe09811	FTD traceback and reload during policy deployment adding/removing/editing of NAT statements.
CSCwe10290	FTD is dropping GRE traffic from WSA
CSCwe10548	ASA binding with LDAP as authorization method with missing configuration
CSCwe11119	ASA: Traceback and reload while processing SNMP packets
CSCwe12407	High Lina memory use due to leaked SSL handles
CSCwe12705	multimode-tmatch_df_hijack_walk traceback observed during shut/unshut on FO connected switch interfa
CSCwe14174	FTD - 'show memory top-usage' providing improper value for memory allocation
CSCwe14417	FTD: IPSLA Pre-emption not working even when destination becomes reachable
CSCwe14514	ASA/FTD Traceback and reload of Standby Unit while removing capture configurations
CSCwe18472	[FTD Multi-Instance][SNMP] - CPU OIDs return incomplete list of associated CPUs
CSCwe18974	ASA/FTD may traceback and reload in Thread Name: CTM Daemon
CSCwe20043	256-byte memory block gets depleted on start if jumbo frame is enabled with FTD on ASA5516
CSCwe20714	Traffic drop when primary device is active
CSCwe20918	Open AC VPN Agent" can connect to a Multi-Cert Auth TG using a single cert & username/password
CSCwe21187	ASA/FTD may drop multicast packets due to no-mcast-intrf ASP drop reason until UDP timeout expires
CSCwe21280	Multicast connection built or teardown syslog messages may not always be generated

Identifier	Headline
CSCwe22302	Partition "/opt/cisco/config" gets full due to wttmp file not getting logrotated
CSCwe23039	NTP polling frequency changed from 5 minutes to 1 second causes large useless log files
CSCwe24532	Multiple instances of nvram.out log rotated files under /opt/cisco/platform/logs/
CSCwe25342	ASA/FTD - SNMP related memory leak behavior when snmp-server is not configured
CSCwe26342	ASA Traceback & reload citing thread name: asacli/0
CSCwe26612	FTD taking longer than expected to form OSPF adjacencies after a failover switchover
CSCwe28094	ASA/FTD may traceback and reload after executing 'clear counters all' when VPN tunnels are created
CSCwe28407	LINA traceback with icmp_thread
CSCwe28726	The command "app-agent heartbeat" is getting removed when deleting any created context
CSCwe29179	CLUSTER: ICMP reply arrives at director earlier than CLU add flow request from flow owner.
CSCwe29529	FTD MI does not adjust PVID on vlans attached to BVI
CSCwe29583	ASA/FTD may traceback and reload in Thread Name 'None' at lua_getinfo
CSCwe29850	ASA/FTD Show chunkstat top command implementation
CSCwe30228	ASA/FTD might traceback in funtion "snp_fp_l2_capture_internal" due to cf_reinject_hide flag
CSCwe30867	Workaround to set hwclock from ntp logs on low end platforms
CSCwe36176	ASA/FTD: High failover delay with large number of (sub)interfaces and http server enabled
CSCwe37453	Gateway is not reachable from standby unit in admin and user context with shared mgmt intf
CSCwe38029	Multiple traceback seen on standby unit.
CSCwe39425	2100: Power switch toggle leads to ungraceful shutdowns and "PowerCycleRequest" reset
CSCwe40463	Stale IKEv2 SA formed during simultaneous IKE SA handling when missing delete from the peer
CSCwe41336	FDM WM-HA ssh is not working after upgrading 7.2.3 beta with data interface as management
CSCwe41898	ASA: FP2100 FTW timeout triggered by high CPU usage during FTD Access Control Policy deploy.

Identifier	Headline
CSCwe42061	Deleting a BVI in FTD interfaces is causing packet drops in other BVIs
CSCwe44311	FP2100:Update LINA asa.log files to avoid recursive messages-<date>.1.gz rotated filenames
CSCwe44672	Syslog ASA-6-611101 is generated twice for a single ssh connection
CSCwe45093	User with no vpn-filter may get additional access when per-user-override is set (IKEv2 RAVPN)
CSCwe45569	FTD upgrade from 7.0 to 7.2.x and beyond crashes due to management-access enabled
CSCwe45779	ASA/FTD drops traffic to BVI if floating conn is not default value due to no valid adjacency
CSCwe50946	Management interface link status not getting synced between FXOS and ASA
CSCwe50993	SNMP on SFR module goes down and won't come back up
CSCwe51286	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwe51443	ASA Evaluation of OpenSSL vulnerability CVE-2022-4450
CSCwe52120	SSL decrypted conns fails when tx chksum-offload is enabled with the egress interface a pppoe.
CSCwe54529	FTD on FPR2140 - Lina traceback and reload by TCP normalization
CSCwe58207	Memory leak observed on ASA/FTD when logging history is enabled
CSCwe58700	ASA/FTD: Revision of cluster event message "Health check detected that control left cluster"
CSCwe59380	FTD: "timeout floating-conn" not operating as expected for connections dependent on VRF routing
CSCwe59737	ASA/FTD reboots due to traceback pointing to watchdog timeout on p3_tree_lookup
CSCwe59919	FTD Traceback and reload on Thread Name "NetSnmp Event mib process"
CSCwe61928	PIM register packets are not sent to RP after a reload if FTD uses a default gateway to reach the RP
CSCwe61969	ASA Multicontext 'management-only' interface attribute not synced during creation
CSCwe62361	ASA reboots due to heartbeat loss and "Communication with NPU lost"
CSCwe62703	New context subcommands are not replicated on HA standby when multiple sessions are opened.
CSCwe62971	Policy Deploy Failing when trying to remove Umbrella DNS Connector Configuration
CSCwe62997	ASA/FTD traceback in snp_tracer_format_route

Identifier	Headline
CSCwe63067	ASA/FTD may traceback and reload in Thread Name 'lina' due to due to tcp intercept stat
CSCwe63232	ASA/FTD: Ensure flow-offload states within cluster are the same
CSCwe63266	Need fault/error for invalid firmware MF-111-234949
CSCwe64043	Cisco ASA and FTD ACLs Not Installed upon Reload
CSCwe64404	ASA/FTD may traceback and reload
CSCwe64557	ASA: Prevent SFR module configuration on unsupported platforms
CSCwe64563	The command "neighbor x.x.x.x ha-mode graceful-restart" removed when deleting any created context
CSCwe65245	FP2100 series devices might use excessive memory if there is a very high SNMP polling rate
CSCwe65492	KP Generating invalid core files which cannot be decoded 7.2.4-64
CSCwe65634	ASA - Standby device may traceback and reload during synchronization of ACL DAP
CSCwe66132	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwe67751	Last fragment from SIP IPv6 packets has MF equal to 1, flagging that more packets are expected
CSCwe67816	ASA / FTD Traceback and reload when removing isakmp capture
CSCwe68159	Failover fover_trace.log file is flooding and gets overwritten quickly
CSCwe70202	Multiple times the failover may be disabled by wrongly seeing a different "Mate operational mode".
CSCwe70378	Connections not replicated to Standby FTD
CSCwe71220	FTD 3100 Crash in Thead Name: CP Processing
CSCwe71284	ASA/FTD may traceback and reload in Thread Name DATAPATH-3-21853
CSCwe72535	Unable to login to FTD using external authentication
CSCwe73116	Cross-interface-access: ICMP Ping to management access ifc over VPN is broken
CSCwe74059	logrotate is not compressing files on 9.16 ASA or 7.0 FTD
CSCwe74089	ASA/FTD may traceback and reload in Thread Name DATAPATH-1-1656
CSCwe74328	AnyConnect - mobile devices are not able to connect when hostscan is enabled
CSCwe74916	Interface remains DOWN in an Inline-set with propagate link state
CSCwe76722	ASA/FTD: From-the-box ping fails when using a custom VRF

Identifier	Headline
CSCwe77123	ASA/FTD : Degradation for TCP tput on FPR2100 via IPSEC VPN when there is delay between VPN peers
CSCwe78977	ASA/FTD may traceback and reload in Thread Name 'pix_flash_config_thread'
CSCwe79072	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwe80063	Default DLY value of port-channel sub interface mismatch with parent Portchannel
CSCwe81684	ASA: Standby failure on parsing of "management-only" not reported to parser/failover subsystem
CSCwe82704	PortChannel sub-interfaces configured as data/data-sharing, in multi-instance HA go into "waiting"
CSCwe83255	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwe85432	ASA/FTD traceback and reload on thread DATAPATH-14-11344 when SIP inspection is enabled
CSCwe86225	ASA/FTD traceback and reload due citing thread name: cli_xml_server in tm_job_add
CSCwe87134	Lina core created during high traffic testing
CSCwe88772	ASA traceback and reload with process name: cli_xml_request_process
CSCwe89030	Serial number attribute from the subject DN of certificate should be taken as the username
CSCwe89731	Notification Daemon false alarm of Service Down
CSCwe90095	Username-from-certificate feature cannot extract the email attribute
CSCwe90202	ASA: Standby failure on parsing of "management-only" for dynamic configuraiton changes
CSCwe90720	ASA Traceback and reload in parse thread due ha_msg corruption
CSCwe92905	ngfwManager process continuously restarting leading to ZMQ Out of Memory traceback
CSCwe93202	FXOS REST API: Unable to create a keyring with type "ecdsa"
CSCwe93489	Threat-detection does not recognize exception objects with a prefix in IPv6
CSCwe93532	ASA/FTD may traceback and reload in Thread Name 'lina'.
CSCwe93537	Threat-detection does not allow to clear individual IPv6 entries
CSCwe93561	Cisco ASA and FTD VPN Web Client Services Client-Side Request Smuggling Vulnerability
CSCwe94287	FTD DHCP Relay drops NACK if multiple DHCP Servers are configured
CSCwe95729	Cisco ASA & FTD SAML Authentication Bypass Vulnerability

Identifier	Headline
CSCwe95757	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwe96023	ASa/FTD: SNMP related traceback and reload immediately after upgrade from 6.6.5 to 7.0.1
CSCwe96068	ASA: Configurable CLU for Large amount of under/overruns on CLU RX/TX queues
CSCwe97277	Observed ASA traceback and reload when performing hitless upgrade while VPN traffic running
CSCwe98687	7.2.4 - Block depletion using single crafted UDP SIP register request
CSCwe99040	traceback and reload thread datapath on process tcpmod_proxy_continue_bp
CSCwe99550	Add knob to pause/resume file specific logging in asa log infra.
CSCwf00865	FTD/ASA Hub and spoke (U-turn) VPN fails when one spoke is IPsec flow offloaded and the other isn't
CSCwf01064	TCP ping is completely broken starting in 9.18.2
CSCwf04831	ASA/FTD may traceback and reload in Thread Name 'ci/console'
CSCwf04870	ASA: "Ping <ifc_name> x.x.x.x" is not working as expected starting 9.18.x
CSCwf05295	FTD running on FP1000 series might drop packets on TLS flows after the "Client Hello" message.
CSCwf06377	Setting heartbeat timeout to 6sec for BS and QP
CSCwf07791	ASA running out of SNMP PDU and SNMP VAR chunks
CSCwf08043	Lina traceback and reload due to fragmented packets
CSCwf08515	FPR3100: ASA/FTD High traffic impact on all data interfaces with high counter of "demux drops"
CSCwf10910	FTD : Traceback in ZMQ running 7.3.0
CSCwf12005	ASA sends OCSP request without user-agent and host
CSCwf12408	ASA: After upgrade to 9.16.4 all type-8 passwords are lost on first reboot
CSCwf12985	FTDv: Traffic failure in VMware Deployments due to dpdk pool exhaustion and rx_buff_alloc_failure
CSCwf14126	ASA Traceback and reload citing process name 'lina'
CSCwf14735	traceback and reload in Process Name: lina related to Nat/Pat
CSCwf14811	TCP normalizer needs stats that show actions like packet drops
CSCwf15858	LDAP authentication over SSL not working for users that send large authorisation profiles

Identifier	Headline
CSCwf15863	Very specific "vpn-idle-timeout" values cause continuous SSL session disconnects and reconnects
CSCwf15902	ASAv in Hyper-V drops packets on management interface
CSCwf17042	ASDM replaces custom policy-map with default map on class inspect options at backup restore.
CSCwf17814	ASA/FTD may traceback and reload in Thread Name '19', free block checksum failure
CSCwf20338	ASA may traceback and reload in Thread Name 'DHCPv6 Relay'
CSCwf21106	ASA/FTD: Traceback on thread name: snmp_master_callback_thread during SNMP and interface changes
CSCwf22005	ASA Packet-tracer displays the first ACL rule always, though matches the right ACL
CSCwf22483	SSH to Chassis allows a 3-way handshake for IPs that are not allowed by the config
CSCwf23564	Unable to establish BGP when using MD5 authentication over GRE TUNNEL and FTD as passthrough device
CSCwf26407	FP2130- Unable to disassociate member from port channel, deployment fails, member is lost on FTD/FMC
CSCwf26534	ASA/FTD: Connection information in SIP-SDP header remains untranslated with destination static Any
CSCwf26939	FTD may fail to create a NAT rule with error: "IPv4 dst real obj address range is huge"
CSCwf28488	Inconsistent log messages seen when emblem is configured and buffer logging is set to debug
CSCwf30716	ASA in multi context shows standby device in failed stated even after MIO HB recovery.
CSCwf30727	ASA integration with umbrella does not work without validation-usage ssl-server.
CSCwf30824	Add CIMC reset as auto-recovery for CIMC IPMI hung issues
CSCwf31701	ASA traceback and reload with the Thread name: **CP Crypto Result Processing**
CSCwf31820	Firewall may drop packets when routing between global or user VRFs
CSCwf33574	ASA access-list entries have the same hash after upgrade
CSCwf33904	[IMS_7_4_0] - Virtual FDM Upgrade fails: HA configStatus='OUT_OF_SYNC after UpgradeOnStandby
CSCwf34500	FTD: GRE traffic is load balanced between CPU cores
CSCwf35207	ASA: Traceback and reload while updating ACLs on ASA
CSCwf35233	Cisco Adaptive Security Appliance Software and Firepower Threat Defense DoS

Identifier	Headline
CSCwf35500	FXOS/SSP: System should provide better visibility of DIMM Correctable error events
CSCwf35573	Traffic may be impacted if TLS Server Identity probe timeout is too long
CSCwf37160	AnyConnect Ikev2 Login Failed With certificate-group-map Configured
CSCwf39163	ASAv - High latency is experienced on Azure environment for ICMP ping packets while running snmpwalk
CSCwf42144	ASA/FTD may traceback and reload citing process name "lina"
CSCwf43288	Traceback in Thread Name: ssh/client in a clustered setup
CSCwf43537	Lina crash in thread name: cli_xml_request_process during FTD cluster upgrade
CSCwf44537	99.20.1.16 lina crash on nat_remove_policy_from_np
CSCwf47227	Priority-queue command causes silent egress packet drops on all port-channel interfaces
CSCwf47924	Cisco ASA and FTD VPN Web Client Services Client-Side Request Smuggling Vulnerability
CSCwf48599	VPN load-balancing cluster encryption using deprecated ciphers
CSCwf49573	ASA/FTD: Traceback and reload when issuing 'show memory webvpn all objects'
CSCwf50497	DNS cache entry exhaustion leads to traceback
CSCwf51933	FTD username with dot fails AAA-RADIUS external authentication login after upgrade
CSCwf52810	ASA SNMP polling not working and showing "Unable to honour this request now" on show commands
CSCwf54418	Reduce time taken to clear stale IKEv2 SAs formed after Duplicate Detection
CSCwf54510	ASA traceback and reload on Thread Name: DHCPRA Monitor
CSCwf56811	ASA Traceback & reload on process name lina due to memory header validation
CSCwf58876	KP2140-HA, reloaded primary unit not able to detect the peer unit
CSCwf59571	FTD/Lina - ZMQ issue OUT OF MEMORY. due to less Msglyr pool memory in low end platforms
CSCwf60311	ASA generating traceback with thread-name: DATAPATH-53-18309 after upgrade to 9.16.4.19
CSCwf60590	"show route all summary" executed on transparent mode FTD is causing CLISH to become Sluggish.
CSCwf62729	Lina Crash in RAVPN interface with anomaly traffic in both non-FIPS and FIPS mode
CSCwf62885	FTDv Single-Arm Proxy behind AWS GWLB drops due to geneve-invalid-udp-checksum.

Identifier	Headline
CSCwf63872	FTD taking longer than expected to form OSPF adjacencies after a failover switchover
CSCwf71606	Cisco ASA and FTD ACLs Not Installed upon Reload
CSCwf71812	FTD Lina engine may traceback, due to assertion, in datapath
CSCwf72434	Add meaningful logs when the maximums system limit rules are hit
CSCwf72510	Avoid both the devices in HA sends events to FMC
CSCwf73189	FTD is dropping GRE traffic from WSA due to NAT failure
CSCwf73773	Dumping of last 20 rmu request response packets failed
CSCwf75214	ASA removes the IKEv2 Remote PSK if the Key String ends with a backslash "\" after reload
CSCwf77191	ASA appliance mode - 'connect fxos [admin]' will get ERROR: failed to open connection.
CSCwf78321	ASA: Checkheaps traceback and reload due to Clientless WebVPN
CSCwf81058	FTD: Firepower 3100 Dynamic Flow Offload showing as Enabled
CSCwf82247	Policy deployment fails when a route same prefix/metric is configured in a separate VRF.
CSCwf85757	Cisco ASA Software and FTD Software SAML Assertion Hijack Vulnerability
CSCwf87070	WM RM - SFP port status of 9 follows port of state of SFP 10 11 12
CSCwf88124	switch ports in Trunk mode do not pass vlan traffic after power loss
CSCwf88552	ASA/FTD: Traceback and reload due to NAT L7 inspection rewrite
CSCwf92135	ASA: Traceback and reload on Tread name "fover_FSM_thread" and ha_ntfy_prog_process_timer
CSCwf92646	ECDSA Self-signed certificate using SHA384 for EC521
CSCwf94677	"failover standby config-lock" config is lost after both HA units are reloaded simultaneously
CSCwf95147	OSPFv3 Traffic is Centralized in Transparent Mode
CSCwf96938	FMC: ACP Rule with UDP port 6081 is getting removed after subsequent deployment
CSCwh00692	Traceback @<capture_file_show+605 at ../infrastructure/capture/capture_file_finesse.c:282>
CSCwh02457	Radius authentication stopped working after ASAv on AWS upgrade to any higher version than 9.18.2

Resolved Bugs in Version 9.18(3)

Identifier	Headline
CSCwh04365	ASA Traceback & reload on process name lina due to memory header validation - webvpn side fix
CSCwh04395	ASDM application randomly exits/terminates with an alert message on multi-context setup
CSCwh04730	ASA/FTD HA checkheaps crash where memory buffers are corrupted
CSCwh06452	Interface speed mismatch in SNMP response using OID .1.3.6.1.2.1.2.2
CSCwh08481	ASA traceback on Lina process with FREEB and VPN functions
CSCwh08683	FTDv/AWS - NTP clock offset between Lina and FTD cluster
CSCwh11764	ASA/FTD may traceback and reload in Thread Name "RAND_DRBG_bytes" and CTM function on n5 platforms
CSCwh13474	PSEQ (Power-Sequencer) firmware - remove device-id check
CSCwh13821	ASA/FTD may traceback and reload in when changing capture buffer size
CSCwh23100	Cisco ASA and FTD Software Remote Access VPN Unauthorized Access Vulnerability
CSCwh23100	Cisco ASA and FTD Software Remote Access VPN Unauthorized Access Vulnerability
CSCwh23567	PAC Key file missing on standby on reload
CSCwh27230	Connections are not cleared after idle timeout when the interfaces are in inline mode.
CSCwh28144	Specific OID 1.3.6.1.2.1.25 should not be responding
CSCwh30891	ASA/FTD may traceback and reload in Thread Name 'ssh' when adding SNMPV3 config
CSCwh31495	FTD - Traceback and reload due to nat rule removed by CPU core
CSCwh37733	FTD responding to UDP500 packet with a Mac Address of 0000.000.000
CSCwh41127	ASA/FTD: NAT64 error "overlaps with inside standby interface address" for Standalone ASA
CSCwh45108	Cisco ASA and FTD Software Remote Access VPN Unauthorized Access Vulnerability
CSCwh45108	Cisco ASA and FTD Software Remote Access VPN Unauthorized Access Vulnerability
CSCwh49483	ASA/FTD may traceback and reload while running show inventory all

Resolved Bugs in Version 9.18(3)

The following table lists select resolved bugs at the time of this Release Note publication.

Identifier	Headline
CSCvz34289	In some cases transition to lightweight proxy doesn't work for Do Not Decrypt flows

Identifier	Headline
CSCvz36903	ASA traceback and reload while allocating a new block for cluster keepalive packet
CSCvz41551	FP2100: ASA/FTD with threat-detection statistics may traceback and reload in Thread Name 'lina'
CSCvz71596	"Number of interfaces on Active and Standby are not consistent" should trigger warning syslog
CSCwa04262	Cisco ASA Software SSL VPN Client-Side Request Smuggling Vulnerability via "/"URI
CSCwa36535	Standby unit failed to join failover due to large config size.
CSCwa59907	LINA observed traceback on thread name "snmp_client_callback_thread"
CSCwa72929	SNMPv3 polling may fail using privacy algorithms AES192/AES256
CSCwa74063	Disable NLP rules installation workaround after mgmt-access into NLP is enabled
CSCwa82850	ASA Failover does not detect context mismatch before declaring joining node as "Standby ready"
CSCwa97917	ISA3000 in boot loop after powercycle
CSCwb00871	ENH: Reduce latency in log_handler_file to reduce watchdog under scale or stress
CSCwb03704	ASA/FTD datapath threads may run into deadlock and generate traceback
CSCwb04000	ASA/FTD: DF bit is being set on packets routed into VTI
CSCwb05291	Cisco ASDM and ASA Software Client-side Arbitrary Code Execution Vulnerability
CSCwb31551	When inbound packet contains SGT header, FPR2100 cannot distribute properly per 5 tuple
CSCwb44848	ASA/FTD Traceback and reload in Process Name: lina
CSCwb89963	ASA Traceback & reload in thread name: Datapath
CSCwc02488	ASA/FTD may traceback and reload in Thread Name 'None'
CSCwc03069	Interface internal data0/0 is up/up from cli but up/down from SNMP polling
CSCwc03332	FTD on FP2100 can take over as HA active unit during reboot process
CSCwc03507	No-buffer drops on Internal Data interfaces despite little evidence of CPU hog
CSCwc07262	Standby ASA goes to booting loop during configuration replication after upgrade to 9.16(3).
CSCwc08646	User without password prompted to change password when logged in from SSH Client
CSCwc10145	FTDv Cluster unit not re-joining cluster with error msg "Failed to open NLP SSL listening socket"

Identifier	Headline
CSCwc10241	Temporary HA split-brain following upgrade or device reboot
CSCwc10483	ASA/FTD - Traceback in Thread Name: appAgent_subscribe_nd_thread
CSCwc11511	FTD: SNMP failures after upgrade to 7.0.2
CSCwc11597	ASA tracebacks after SFR was upgraded to 6.7.0.3
CSCwc13017	FTD/ASA traceback and reload at at ../inspect/proxy.h:439
CSCwc18524	ASA/FTD Voltage information is missing in the command "show environment"
CSCwc23844	ASAv high CPU and stack memory allocation errors despite over 30% free memory
CSCwc24906	ASA/FTD traceback and reload on Thread id: 1637
CSCwc26648	ASA/FTD Traceback and Reload in Thread name Lina or Datatath
CSCwc27846	Traceback and Reload while HA sync after upgrading and reloading.
CSCwc28334	Cisco ASA and FTD Software RSA Private Key Leak Vulnerability
CSCwc28532	9344 Block leak due to fragmented GRE traffic over inline-set interface inner-flow processing
CSCwc28806	ASA Traceback and Reload on process name Lina
CSCwc28928	ASA: SLA debugs not showing up on VTY sessions
CSCwc31457	ASA process with cleartext token when not able to encrypt it
CSCwc32246	NAT64 translates all IPv6 Address to 0.0.0.0/0 when object subnet 0.0.0.0 0.0.0.0 is used
CSCwc36905	ASA traceback and reload due to "Heap memory corrupted at slib_malloc.c
CSCwc37256	SSL AnyConnect access blocked after upgrade
CSCwc38567	ASA/FTD may traceback and reload while executing SCH code
CSCwc40352	Lina Netflow sending permitted events to Stealthwatch but they are block by snort afterwards
CSCwc40381	ASA : HTTPS traffic authentication issue with Cut-through Proxy enabled
CSCwc44289	FTD - Traceback and reload when performing IPv4 & IPv6 NAT translations
CSCwc45108	ASA/FTD: GTP inspection causing 9344 sized blocks leak
CSCwc45397	ASA HA - Restore in primary not remove new interface configuration done after backup
CSCwc45575	ASA/FTD traceback and reload when ssh using username with nopassword keyword

Identifier	Headline
CSCwc47962	ASA: 'no monitor-interface service-module' command gone after reload.
CSCwc48375	Inbound IPSEC SA stuck inactive - many inbound SPIs for one outbound SPI in "show crypto ipsec sa"
CSCwc49095	ASA/FTD 2100 platform traceback and reload when fragments are coalesced and sent to PDTS
CSCwc50887	FTD - Traceback and reload on NAT IPv4<>IPv6 for UDP flow redirected over CCL link
CSCwc50891	MPLS tagging removed by FTD
CSCwc51326	FXOS-based Firepower platform showing 'no buffer' drops despite high values for RX ring watermarks
CSCwc52351	ASA/FTD Cluster Split Brain due to NAT with "any" and Global IP/range matching broadcast IP
CSCwc53280	ASA parser accepts incomplete network statement under OSPF process and is present in show run
CSCwc54217	syslog related to failover is not outputted in FPR2140
CSCwc54984	IKEv2 rekey - Responding Invalid SPI for the new SPI received right after Create_Child_SA response
CSCwc60037	ASA fails to rekey with IPSEC ERROR: Failed to allocate an outbound hardware context
CSCwc61912	ASA/FTD OSPFv3 does not generate messages Type 8 LSA for IPv6
CSCwc64923	ASA/FTD may traceback and reload in Thread Name 'lina' ip routing ndbshr
CSCwc66757	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwc67687	ASA HA failover triggers HTTP server restart failure and ASDM outage
CSCwc67886	ASA/FTD may traceback and reload in Thread Name 'lina_inotify_file_monitor_thread'
CSCwc70962	FTD/ASA "Write Standby" enables ECDSA ciphers causing AC SSLv3 handshake failure
CSCwc72155	ASA/FTD Traceback and reload on function "snp_cluster_trans_allocb"
CSCwc72284	TACACS Accounting includes an incorrect IPv6 address of the client
CSCwc73224	Call home configuration on standby device is lost after reload
CSCwc74103	ASA/FTD may traceback and reload in Thread Name 'DATAPATH-11-32591'
CSCwc74858	FTD - Traceback in Thread Name: DATAPATH
CSCwc77519	FPR1120-ASA:Primary takes active role after reloading

Identifier	Headline
CSCwc77680	ASA/FTD may traceback and reload in Thread Name 'DATAPATH-0-4948'
CSCwc77892	CGroups errors in ASA syslog after startup
CSCwc79366	During the deployment time, device got stuck processing the config request.
CSCwc80234	"inspect snmp" config difference between active and standby
CSCwc81184	ASA/FTD traceback and reload caused by SNMP process failure
CSCwc81945	Traffic on data unit gets dropped with "LU allocate xlate failed" on GCP cluster with interface NAT
CSCwc81960	Unable to configure 'match ip address' under route-map when using object-group in access list
CSCwc82124	ASA NAT rules are not working as expected after an upgrade to 9.18.2
CSCwc82188	FTD Traceback and reload when applying long capture commands from FMC UI
CSCwc83346	ASA/FTD Traceback and reload in Threadname: IKE Daemon
CSCwc88897	ASA traceback and reload due to null pointer in Umbrella after modifying DNS inspection policy
CSCwc89924	FXOS ASA/FTD SNMP OID to poll Internal-data 'no buffer' interface counters
CSCwc90091	ASA 9.12(4)47 with user-statistics, will affects the "policy-server xxxx global" visibility.
CSCwc93166	Using write standby in a user context leaves secondary firewall license status in an invalid state
CSCwc93964	ASA using WebVPN tracebacks in Unicorn thread during memory tracking
CSCwc94085	Unable to establish DTLSv1.2 with FIPS enabled after upgrade from 6.6.5.
CSCwc94466	Cisco ASA/FTD Firepower 2100 SSL/TLS Denial of Service Vulnerability
CSCwc94501	ASA/FTD tracebacks due to ctm_n5 resets
CSCwc94547	Lina Traceback and reload when issuing 'debug menu fxos_parser 4'
CSCwc95290	ESP rule missing in vpn-context may cause IPSec traffic drop
CSCwc96805	traceback and reload due to tcp intercept stat in thread unicorn
CSCwc99242	ISA3000 LACP channel member SFP port suspended after reload
CSCwd00386	ASA/FTD may traceback and reload when clearing the configuration due to "snp_clear_acl_log_flow_all"
CSCwd00778	ifAdminStatus output is abnormal via snmp polling

Identifier	Headline
CSCwd02864	Changing the buffer size impacting logging to buffer
CSCwd03793	FTD Traceback and reload
CSCwd03810	ASA Custom login page is not working through webvpn after an upgrade
CSCwd04210	ASA: ASDM sessions stuck in CLOSE_WAIT causing lack of MGMT
CSCwd05756	FTD traceback on Lina due to syslog component.
CSCwd06005	ASA/FTD Cluster Traceback and Reload during node leave
CSCwd09870	AnyConnect SAML using external browser and round robin DNS intermittently fails
CSCwd11303	ASA might generate traceback in ikev2 process and reload
CSCwd11855	ASA/FTD may traceback and reload in Thread Name 'ikev2_fo_event'
CSCwd14972	ASA/FTD Traceback and Reload in Thread Name: pix_flash_config_thread
CSCwd16294	GTP inspection drops packets for optional IE Header Length being too short
CSCwd16517	GTP drops not always logged on buffer and syslog
CSCwd16689	ASA/FTD traceback due to block data corruption
CSCwd17856	ASA goes for traceback/reload with message - snmp_ma_kill_restart: vf is NULL
CSCwd18744	FTD Failure to join HA due to "Other unit has different set of hwidb index"
CSCwd19053	ASA/FTD may traceback with large number of network objects deployment using distribute-list
CSCwd20627	ASA/FTD: NAT configuration deployment failure
CSCwd22349	ASA: Unable to connect AnyConnect Cert based Auth with "periodic-authentication certificate" enabled
CSCwd22907	ASA/FTD High CPU in SNMP Notify Thread
CSCwd23188	ASA/FTD may traceback and reload in Thread Name 'lina'
CSCwd23913	FTD in HA traceback multiple times after adding a BGP neighbour with prefix list.
CSCwd25201	ASA/FTD SNMP traps enqueued when no SNMP trap server configured
CSCwd25256	With TCM enabled new ACL's are not working on ASA if non access-group command disabled twice
CSCwd26867	Device should not move to Active state once Reboot is triggered
CSCwd28236	standby unit using both active and standby IPs causing duplicate IP issues due to nat "any"

Identifier	Headline
CSCwd31181	Lina traceback and reload - VPN parent channel (SAL) has an invalid underlying channel
CSCwd31960	Management access over VPN not working when custom NAT is configured
CSCwd37135	ASA/FTD traceback and reload on thread name fover_fail_check
CSCwd38805	Syslog 106016 is not rate-limited by default
CSCwd39468	LINA Traceback and reload at Thread Name: ci/console
CSCwd40260	Serviceability Enhancement - Unable to parse payload are silently drop by ASA/FTD
CSCwd41083	ASA traceback and reload due to DNS inspection
CSCwd42620	Deploying objects with escaped values in the description might cause all future deployments to fail
CSCwd46780	ASA/FTD: Traceback and reload in Thread Name: appAgent_reply_processor_thread
CSCwd48633	ASA - traceback and reload when Webvpn Portal is used
CSCwd50218	ASA restore is not applying vlan configuration
CSCwd51757	Unable to get polling results using snmp GET for connection rate OID's
CSCwd53135	ASA/FTD: Object Group Search Syslog for flows exceeding threshold
CSCwd53340	FTD PDTS LINA RX queue can become stuck when snort send messages with 4085-4096 bytes size
CSCwd53635	AWS: SSL decryption failing with Geneve tunnel interface
CSCwd56254	"show tech-support" generation does not include "show inventory" when run on FTD
CSCwd56296	FTD Lina traceback and reload in Thread Name 'IP Init Thread'
CSCwd56774	Misleading drop reason in "show asp drop"
CSCwd56995	Clientless Accessing Web Contents using application/octet-stream vs text/plain
CSCwd57698	Recursive panic under lina_duart_write
CSCwd59736	ASA/FTD: Traceback and reload due to SNMP group configuration during upgrade
CSCwd61016	ASA: Standby may get stuck in "Sync Config" status upon reboot when there is EEM is configured
CSCwd62138	ASA Connections stuck in idle state when DCD is enabled
CSCwd62859	Cisco ASA and FTD AnyConnect SSL/TLS VPN Denial of Service Vulnerability
CSCwd63580	FPR2100: Increase in failover convergence time with ASA in Appliance mode

Identifier	Headline
CSCwd63961	AC clients fail to match DAP rules due to attribute value too large
CSCwd64480	Packets through cascading contexts in ASA are dropped in gateway context after software upgrade
CSCwd66815	Lina changes to support CSCwb04975 - Snort3 traceback in daq-pdts while handling FQDN based traffic
CSCwd71254	ASA/FTD may traceback and reload in idfw fqdn hash lookup
CSCwd74116	S2S Tunnels do not come up due to DH computation failure caused by DSID Leak
CSCwd77581	System Crash on ICMPv6 Option Processing
CSCwd82235	LINA Traceback on FPR-1010 under Thread Name: update_cpu_usage
CSCwd84133	ASA/FTD may traceback and reload in Thread Name 'telnet/ci'
CSCwd84868	Observing some devcmd failures and checkheaps traceback when flow offload is not used.
CSCwd85178	AWS ASAv PAYG Licensing not working in GovCloud regions.
CSCwd91421	ASA/FTD may traceback and reload in logging_cfg processing
CSCwd93376	Clientless VPN users are unable to download large files through the WebVPN portal
CSCwd94096	Anyconnect users unable to connect when ASA using different authentication and authorization server
CSCwd95043	Cisco ASA and FTD VPN Web Client Services Client-Side Request Smuggling Vulnerability
CSCwd95908	ASA/FTD traceback and reload, Thread Name: rtcli async executor process
CSCwd97020	ASA/FTD: External IDP SAML authentication fails with Bad Request message

Resolved Bugs in Version 9.18(2)

The following table lists select resolved bugs at the time of this Release Note publication.

Identifier	Headline
CSCvw82067	ASA/FTD 9344 blocks depleted due to high volume of fragmented traffic
CSCvy50598	BGP table not removing connected route when interface goes down
CSCvz36903	ASA traceback and reload while allocating a new block for cluster keepalive packet
CSCvz69729	Unstable client processes may cause LINA zmqio traceback on FTD
CSCwa59907	LINA observed traceback on thread name "snmp_client_callback_thread"

Identifier	Headline
CSCwa75966	ASA: Reload and Traceback in Thread Name: Unicorn Proxy Thread with Page fault: Address not mapped
CSCwa97917	ISA3000 in boot loop after powercycle
CSCwb05291	Cisco ASDM and ASA Software Client-side Arbitrary Code Execution Vulnerability
CSCwb06847	ASA/FTD may traceback and reload in Thread Name 'DATAPATH-9-11543'
CSCwb17963	Unable to identify dynamic rate limiting mechanism & not following msg limit per/sec at syslog server.
CSCwb19648	SNMP queries for crasLocalAddress are not returning the assigned IPs for SSL/DTLS tunnels.
CSCwb52401	Cisco Firepower Threat Defense Software Privilege Escalation Vulnerability
CSCwb53172	FTD: IKEv2 tunnels flaps every 24 hours and crypto archives are generated
CSCwb53328	ASA/FTD Traceback and reload caused by Smart Call Home process sch_dispatch_to_url
CSCwb54791	ASA DHCP server fails to bind reserved address to Linux devices
CSCwb63827	Cisco Adaptive Security Appliance Software and Firepower Threat Defense Software DoS
CSCwb67040	FP4112 4115 Traceback & reload on Thread Name: netfs_thread_init
CSCwb68642	ASA traceback in Thread Name: SXP CORE
CSCwb69503	ASA unable to configure aes128-gcm@openssh.com when FIPS enabled
CSCwb71460	ASA traceback in Thread Name: fover_parse and triggered by snmp related functions
CSCwb73248	FW traceback in timer infra / netflow timer
CSCwb74571	PBR not working on ASA routed mode with zone-members
CSCwb79812	RIP is advertising all connected Anyconnect users and not matching route-map for redistribution
CSCwb80559	FTD offloads SGT tagged packets although it should not
CSCwb80862	ASA/FTD proxy arps any traffic when using the built-in 'any' object in translated destination
CSCwb82796	ASA/FTD firewall may traceback and reload when tearing down IKE tunnels
CSCwb83388	ASA HA Active/standby tracebacks seen approximately every two months.
CSCwb83691	ASA/FTD traceback and reload due to the initiated capture from FMC
CSCwb85633	Snmpwalk output of memory does not match show memory/show memory detail

Identifier	Headline
CSCwb87498	Lina traceback and reload during EIGRP route update processing.
CSCwb90074	ASA: Multiple Context Mixed Mode SFR Redirection Validation
CSCwb90532	ASA/FTD traceback and reload on NAT related function nat_policy_find_location
CSCwb92709	We can't monitor the interface via "snmpwalk" once interface is removed from context.
CSCwb93932	ASA/FTD traceback and reload with timer services assertion
CSCwb94190	ASA graceful shut down when applying ACL's with forward reference feature and FIPS enabled.
CSCwb94312	Unable to apply SSH settings to ASA version 9.16 or later
CSCwb97251	ASA/FTD may traceback and reload in Thread Name 'ssh'
CSCwc02488	ASA/FTD may traceback and reload in Thread Name 'None'
CSCwc03069	Interface internal data0/0 is up/up from cli but up/down from SNMP polling
CSCwc09414	ASA/FTD may traceback and reload in Thread Name 'ci/console'
CSCwc10483	ASA/FTD - Traceback in Thread Name: appAgent_subscribe_nd_thread
CSCwc10792	ASA/FTD IPSEC debugs missing reason for change of peer address and timer delete
CSCwc11597	ASA tracebacks after SFR was upgraded to 6.7.0.3
CSCwc11663	ASA traceback and reload when modifying DNS inspection policy via CSM or CLI
CSCwc13017	FTD/ASA traceback and reload at at ../inspect/proxy.h:439
CSCwc13994	ASA - Restore not remove the new configuration for an interface setup after backup
CSCwc18312	"show nat pool cluster" commands run within EEM scripts lead to traceback and reload
CSCwc23356	ASA/FTD may traceback and reload in Thread Name 'DATAPATH-20-7695'
CSCwc23695	ASA/FTD can not parse UPN from SAN field of user's certificate
CSCwc24422	AC SSLVPN with Certificate Authentication and DAP failure if client's machine cert has empty subject
CSCwc24906	ASA/FTD traceback and reload on Thread id: 1637
CSCwc28532	9344 Block leak due to fragmented GRE traffic over inline-set interface inner-flow processing
CSCwc28928	ASA: SLA debugs not showing up on VTY sessions
CSCwc32246	NAT64 translates all IPv6 Address to 0.0.0.0/0 when object subnet 0.0.0.0 0.0.0.0 is used

Resolved Bugs in Version 9.18(1)

The following table lists select resolved bugs at the time of this Release Note publication.

Identifier	Headline
CSCvw56551	ASA displays cosmetic NAT warning message when making the interface config changes
CSCvw62288	ASA: 256 byte block depletion when syslog rate is high
CSCvx97053	Unable to configure ipv6 address/prefix to same interface and network in different context
CSCvy04430	Management Sessions fail to connect after several weeks
CSCvy40401	L2L VPN session bringup fails when using NULL encryption in ipsec configuration
CSCvz03524	PKI "OCSP revocation check" failing due to sha256 request instead of sha1
CSCvz05541	ASA55XX: Expansion module interfaces not coming up after a software upgrade
CSCvz44645	FTD may traceback and reload in Thread Name 'lina'
CSCvz60578	Cluster unit in MASTER_POST_CONFIG state should transition to Disabled state after an interval
CSCvz68336	SSL decryption not working due to single connection on multiple in-line pairs
CSCvz69729	Unstable client processes may cause LINA zmqio traceback on FTD
CSCvz70688	default-information originate is configured first then Stub command is not allowed for config
CSCvz70958	High Control Plane CPU on StandBy due to dhcpp_add_ip_l_stby
CSCvz72771	ASA/FTD may traceback and reload. "c_assert_cond_terminate" in stack trace
CSCvz76746	While implementing management tunnel a user can use open connect to bypass anyconnect.
CSCvz76966	Cisco Adaptive Security Appliance Software and Firepower Threat Defense Software DNS DoS
CSCvz81888	NTP will not change to *(synced) status after upgrade to asa-9.15.1/9.16.1.28 from asa-9.14.3
CSCvz86256	Primary ASA should send GARP as soon as split-brain is detected and peer becomes cold standby
CSCvz88149	Lina traceback and reload during block free causing FTD boot loop
CSCvz89126	ASDM session/quota count mismatch in ASA when multiple context switchover is done from ASDM
CSCvz89327	OSPFv2 flow missing cluster centralized "c" flag

Identifier	Headline
CSCvz90375	Low available DMA memory on ASA 9.14 at boot reduces AnyConnect sessions supported
CSCvz91218	Statelink hello messages dropped on Standby unit due to interface ring drops on high rate traffic
CSCvz92016	Cisco ASA and FTD Software Web Services Interface Privilege Escalation Vulnerability
CSCvz92932	ASA show tech execution causing spike on CPU and impacting to IKEv2 sessions
CSCvz94153	NTP sync on IPV6 will fail if the IPV4 address is not configured
CSCvz95108	FTD Deployment failure post upgrade due to major version change on device
CSCvz95949	FP1120 9.14.3 : temporary split brain happened after active device reboot
CSCvz99222	Clear and show conn for inline-set is not working
CSCwa02929	FTD Blocks Traffic with SSL Flow Error CORRUPT_MESSAGE
CSCwa03341	Standby's sub interface mac doesn't revert to old mac with no mac-address command
CSCwa08262	AnyConnect users with mapped group-policies take attributes from default GP under the tunnel-group
CSCwa11052	SNMP Stopped Responding After Upgrading to Version- 9.14(2)15
CSCwa13873	ASA Failover Split Brain caused by delay on state transition after "failover active" command run
CSCwa14485	Cisco Firepower Threat Defense Software Denial of Service Vulnerability
CSCwa14725	ASA/FTD traceback and reload on IKE Daemon Thread
CSCwa15185	ASA/FTD: remove unwanted process call from LUA
CSCwa18858	ASA drops non DNS traffic with reason "label length 164 bytes exceeds protocol limit of 63 bytes"
CSCwa18889	Clock drift observed between Lina and FXOS on multi-instance
CSCwa19443	Flow Offload - Compare state values remains in error state for longer periods
CSCwa19713	Traffic dropped by ASA configured with BVI interfaces due to asp drop type "no-adjacency"
CSCwa28822	FTD moving UI management from FDM to FMC causes traffic to fail
CSCwa28895	FTD SSL Decryption Traffic Latency SSL Proxy to allow configurable/dynamic maximum TCP window size
CSCwa30114	"Error:NAT unable to reserve ports" when using a range of ports in an object service

Identifier	Headline
CSCwa33898	Cisco Adaptive Security Appliance Software Clientless SSL VPN Heap Overflow Vulnerability
CSCwa34287	ASA: Loss of NTP sync following a reload after upgrade
CSCwa35200	Some syslogs for AnyConnect SSL are generated in admin context instead of user context
CSCwa36672	ASA on FPR4100 traceback and reload when running captures using ASDM
CSCwa36678	Random FTD reloads with the traceback during deployment from FMC
CSCwa38277	ASA NAT66 with big range as a pool don't works with IPv6
CSCwa40719	Traceback: Secondary firewall reloading in Threadname: fover_parse
CSCwa41834	ASA/FTD traceback and reload due to pix_startup_thread
CSCwa41936	Cisco FTD Bleichenbacher Attack Vulnerability
CSCwa42594	ASA: IP Header check validation failure when GTP Header have SEQ and EXT field
CSCwa47041	Cisco Adaptive Security Appliance Software and Firepower Threat Defense Software DAP DoS
CSCwa49480	SNMP OID , stop working after around one hour and a half - FTD
CSCwa53489	Lina Traceback and Reload Due to invalid memory access while accessing Hash Table
CSCwa54045	Memory leaks in SAML native browser processing
CSCwa55562	Different CG-NAT port-block allocated for same source IP causing per-host PAT port block exhaustion
CSCwa55878	FTD Service Module Failure: False alarm of "ND may have gone down"
CSCwa56449	ASA traceback in HTTP cli EXEC code
CSCwa56975	DHCP Offer not seen on control plane
CSCwa57115	New access-list are not taking effect after removing non-existence ACL with objects.
CSCwa58686	ASA/FTD Change in OGS compilation behavior causing boot loop
CSCwa61218	Polling OID "1.3.6.1.4.1.9.9.171.1.3.2.1.2" gives negative index value of the associated tunnel
CSCwa65389	ASA traceback and reload in Unicorn Admin Handler when change interface configuration via ASDM
CSCwa67882	Offloaded GRE tunnels may be silently un-offloaded and punted back to CPU
CSCwa68660	FTP inspection stops working properly after upgrading the ASA to 9.12.4.x

Identifier	Headline
CSCwa73172	ASA reload and traceback in Thread Name: PIX Garbage Collector
CSCwa74900	Traceback and reload after enabling debug webvpn cifs 255
CSCwa75966	ASA: Reload and Traceback in Thread Name: Unicorn Proxy Thread with Page fault: Address not mapped
CSCwa77073	SNMP is responding to snmpgetbulk with unexpected order of results
CSCwa79494	Traffic keep failing on Hub when IPSec tunnel from Spoke flaps
CSCwa79980	SNMP get command in FPR does not show interface index.
CSCwa81795	Cisco ASA and FTD Software VPN Authorization Bypass Vulnerability
CSCwa85043	Traceback: ASA/FTD may traceback and reload in Thread Name 'Logger'
CSCwa85138	Multiple issues with transactional commit diagnostics
CSCwa87315	ASA/FTD may traceback and reload in Thread Name 'IP Address Assign'
CSCwa89243	SNMP no longer responds to polls after upgrade to 9.15.1.17
CSCwa91090	SSL handshake logging showing unknown session during AnyConnect TLSv1.2 Session establishment
CSCwa94894	ASA/FTD may traceback and reload in Thread Name 'DATAPATH-4-9608'
CSCwa96759	Lina may traceback and reload on tcpmod_proxy_handle_mixed_mode
CSCwa97784	ASA: Jumbo sized packets are not fragmented over the L2TP tunnel
CSCwa98684	Console has an excessive rate of warnings during policy deployment
CSCwb00595	Mempool_DMA allocation issue / memory leakage
CSCwb01700	ASA: SSH and ASDM sessions stuck in CLOSE_WAIT causing lack of MGMT for the ASA
CSCwb01919	FP2140 ASA 9.16.2 HA units traceback and reload at lua_getinfo (getfuncname)
CSCwb08644	Crash at IKEv2 from Scaled S2S+AC-DTLS+SNMP long duration test
CSCwb11939	ASA/FTD MAC modification is seen in handling fragmented packets with INSPECT on
CSCwb16920	CPU profile cannot be reactivated even if previously active memory tracking is disabled
CSCwb18252	FTD/ASA: Traceback on BFD function causing unexpected reboot
CSCwb25809	Single Pass - Traceback due to stale ifc
CSCwb54791	ASA DHCP server fails to bind reserved address to Linux devices

Identifier	Headline
CSCwb66761	Cisco Firepower Threat Defense Software Generic Routing Encapsulation DoS Vulnerability
CSCwb69503	ASA unable to configure aes128-gcm@openssh.com when FIPS enabled
CSCwb80862	ASA/FTD proxy arps any traffic when using the built-in 'any' object in translated destination
CSCwb85633	Snmpwalk output of memory does not match show memory/show memory detail

Cisco General Terms

The Cisco General Terms (including other related terms) governs the use of Cisco software. You can request a physical copy from Cisco Systems, Inc., P.O. Box 641387, San Jose, CA 95164-1387. Non-Cisco software purchased from Cisco is subject to applicable vendor license terms. See also: <https://cisco.com/go/generalterms>.

Related Documentation

For additional information on the ASA, see [Navigating the Cisco Secure Firewall ASA Series Documentation](#).

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2024 Cisco Systems, Inc. All rights reserved.