

HDDステータスを[Unconfigured good]から[JBOD]に変更できない

内容

[概要](#)

[前提条件](#)

[要件](#)

[使用するコンポーネント](#)

[背景説明](#)

[トラブルシューティングの手順](#)

[解決方法](#)

[関連情報](#)

概要

この記事では、パススルーコントローラUCSC-SAS12GHBAがJBODモードのみをサポートしているため、HDDの状態を[Unconfigured good]から[JBOD]に変更できないシナリオについて説明します

前提条件

要件

このドキュメントに特有の要件はありません。

使用するコンポーネント

- UCSC-C220-M4L
- CIMC:3.0.3a
- UCS-HD12TB10KHY-E X 2
- RAIDコントローラ：UCSC-SAS12GHBAをパススルー

このドキュメントの情報は、特定のラボ環境にあるデバイスに基づいて作成されました。このドキュメントで使用するすべてのデバイスは、初期（デフォルト）設定の状態から起動しています。本稼働中のネットワークでは、各コマンドによって起こる可能性がある影響を十分確認してください。

背景説明

UCSC-240C-M4L仕様を参照してください

■ Cisco 12 Gbps Modular SAS HBA with internal SAS connectivity

- Supports up to 24 internal drives (only 4 drives supported in this server)
- Plugs into a dedicated PCIe slot at the rear of the server (slot 1 of riser 1)
- Supports JBOD only, not RAID, as shown in the below table.

トラブルシューティングの手順

1. UCS-HD12TB10KHY-Eは、UCSC-C220-M4Lのスペックシートに従って、コントローラUCSC-SAS12GHBAでサポートされます。

<https://www.cisco.com/c/dam/en/us/products/collateral/servers-unified-computing/ucs-c-series-rack-servers/c220m4-lff-spec-sheet.pdf>

(2) Cisco 12 Gbps Modular SAS HBA

- If you selected a Cisco 12 Gbps Modular SAS HBA you have the following option:
 - Select up to 4 HDDs listed in [Table 10](#).

Table 10 Available Hot-Pluggable Sled-Mounted HDDs

Product ID (PID)	PID Description	Drive Type	Capacity
HDDs			
UCS-HD8T7KEM	8 TB 12G SAS 7.2K RPM LFF HDD (512e)	SAS	8 TB
UCS-HD4T7KL12G	4 TB 12G SAS 7.2K RPM LFF HDD	SAS	4 TB
UCS-HD2T7KL12G	2 TB 12G SAS 7.2K RPM LFF HDD	SAS	2 TB
UCS-HD10T7KEM	10 TB 12G SAS 7.2K RPM LFF HDD (512e)	SAS	10 TB
UCS-HD6T7KEM	6 TB 12G SAS 7.2K RPM LFF HDD (512e)	SAS	6 TB
UCS-HD1T7KL12G	1 TB 12G SAS 7.2K RPM LFF HDD	SAS	1 TB
UCS-HD10T7KL4K ¹	10 TB 12G SAS 7.2K RPM LFF HDD (4K sector format)	SAS	10 TB
UCS-HD8T7KL4K ¹	8 TB 12G SAS 7.2K RPM LFF HDD (4K sector format)	SAS	8 TB
UCS-HD6T7KL4K ¹	6 TB 12G SAS 7.2K RPM LFF HDD (4K sector format)	SAS	6 TB
UCS-HD2T7KL6GA	2 TB 6G SATA 7.2K RPM LFF HDD	SATA	2 TB
UCS-HD12TB10KHY-E	1.2 TB 3.5 inch 12G SAS 10K RPM HDD	SAS	1.2 TB
UCS-HD600G15KHY-E	600 GB 3.5 inch Hybrid 6G SAS 15K RPM HDD	SAS	600 GB
UCS-HD300G15KHY-E	300 GB 3.5 inch Hybrid 6G SAS 15K RPM HDD	SAS	300 GB

2. HDDのステータスをJBODに設定/変更するオプションは、[CIMC] > [Inventory] > [Storage] > [Controller/VD]プロパティに存在しません。

Cisco Integrated Management Controller

admin@192.168.4.69 - C220-FCH2139V0V5

/ ... / UCSC-SAS12GHBA (SLOT-HBA) / Physical Drive Info

Controller Info | Physical Drive Info

Physical Drives

Controller	Physical Drive Number	Status	Health	Boot Drive	Drive Firmware	Coerced Size
<input type="checkbox"/> SLOT-HBA	5	Unconfigured	Good	true	N004	1144641 MB
<input type="checkbox"/> SLOT-HBA	6	Unconfigured	Good	false	N004	1144641 MB

Cisco Integrated Management Controller

admin@192.168.4.69 - C220-FCH2139V0V5

/ ... / UCSC-SAS12GHBA (SLOT-HBA) / Controller Info

Preboot CLI Version: N/A
 NITELX version: N/A
 Web BIOS Version: N/A
 NVDATA Version: 0b.01.00.0f
 Boot Block Version: N/A
 Boot Version: N/A

Physical Drive Count

Disk Present Count: 2
 Critical Disk Count: 0
 Failed Disk Count: 0

Controller Info | Physical Drive Info

Clear Boot Drive

Health/Status

Composite Health: ✔ Good
 Controller Status: Optimal
 Chip Temperature: 41

Firmware Versions

Product Name: UCSC-SAS12GHBA
 Serial Number: 580bcbeac420800
 Firmware Package Build: 11.00.00.10

PCI Info

PCI Slot: SLOT-HBA
 Vendor ID: 1000
 Device ID: 0000

HW Configuration

Controller SAS Address: 580bcbeac420800
 Flash Present: true
 Flash Size: 0 MB
 Number Of Backend Ports: 0

Error Counters

Memory Correctable Errors: 0
 Memory Uncorrectable Errors: 0

3. CLIからコントローラ設定のステータスを確認し、コントローラに[JBOD is Enabled]と表示されます。

```
C220-FCH2139V0V5 /chassis/storageadapter # show settings
PCI Slot SLOT-HBA:
  Info Valid: Yes
  Enable JBOD Mode: true
  Info Invalid Cause:
  Predictive Fail Poll Interval: 0 sec
  Rebuild Rate: 0 %
  Patrol Read Rate: 0 %
  Consistency Check Rate: 0 %
  Reconstruction Rate: 0 %
  Cache Flush Interval: 0 sec
  Max Drives to Spin Up at Once: 0
  Delay Among Spinup Groups: 0 sec
  Physical Drive Coercion Mode: None
  Cluster Mode: false
  Battery Warning: false
  ECC Bucket Leak Rate: 0 min
  Expose Enclosure Devices: false
  Maintain PD Fail History: false
  Enable Copyback on SMART: false
  Enable Copyback to SSD on SMART Error: false
  Native Command Queuing: enabled
  Enable Spin Down of Unconfigured Drives: false
  Enable SSD Patrol Read: false
  AutoEnhancedImport: false
C220-FCH2139V0V5 /chassis/storageadapter #
```

4. CIMC CLIからHDDステータスをJBODに変更/設定できるオプションはありません。

5. サーバがリブートすると、UCSC-SAS12GHBAのWeb BIOSユーティリティにアクセスするためにCTRL+Cを選択するように求められます。

しかし、WebBIOSから物理ドライブのステータスを変更するオプションはありません。

解決方法

パススルーコントローラUCSC-SAS12GHBAによって管理されている場合、HDDは「Unconfigured Good」状態のままになります。

Windows 2012 R2を正常なドライブ(HDD#1)にインストールすると、インストールが完了しました。

ドライブの取り付け後 – HDD#1はUnconfigured Good状態のままになります。

関連情報

[CSCvi74706](#): CIMC GUI - Physical drive state displayed Unconfigured Good with UCSC-SAS12GHBA