

SPA3102 IVR(Interactive Voice Response) 메뉴 액세스

목표

인터랙티브 음성 응답에서는 디바이스 내의 다양한 컨피그레이션에 대한 지침을 제공합니다. 이러한 지침은 전화기가 장치에 연결될 때 얻습니다. 이 문서에서는 SPA3102의 IVR(Interactive Voice Response) 메뉴에 대해 더 자세히 설명합니다.

적용 가능한 디바이스

- SPA8000
- SPA3102
- SPA9000
- SPA2102
- SPA112
- PAP2T

소프트웨어 버전

- v6.1.12

IVR(Interactive Voice Response) 메뉴

대화형 음성 응답 메뉴 액세스

1단계. 음성 게이트웨이의 PHONE 포트에 연결된 전화기를 사용합니다. Interactive Voice Response Menu(인터랙티브 음성 응답 메뉴)는 아날로그 전화를 통해서만 액세스할 수 있습니다.

2단계. 4개의 별표(*) 키를 누릅니다.

3단계. 음성 메시지가 나타날 때까지 "Linksys 구성 메뉴"라고 응답합니다. 옵션 뒤에 #(파운드) 키를 입력하거나 "종료하려면 전화를 끊으십시오."

4단계. 작업, 명령, 메뉴 선택 및 설명을 나열하는 다음 표를 참조하십시오. 옵션을 선택한 후 #(파운드) 키를 누릅니다. 메뉴를 종료하려면 전화를 끊습니다.

대화형 음성 응답 메뉴

IVR Action	IVR Menu	Parameter(s)	Notes
Activate IVR Menu	****	None	Ignore SIT or other tones until you hear, "Sipura configuration menu. Please enter option followed by the pound key or hang-up to exit."
Check WAN IP Address	110	None	IVR will announce the IP address of the WAN port
Check WAN Network Mask	120	None	IVR will announce the network mask of the WAN port
Check WAN Gateway	130	None	IVR will announce the gateway of the WAN port
Check MAC Address	140	None	IVR will announce MAC address of the SPA-2100
Check Firmware Version	150	None	IVR will announce the firmware version running on SPA-2100
Check Primary DNS Server IP Address	160	None	IVR will announce the primary DNS server IP address
Check WAN Port Web Server Port	170	None	IVR will announce the WAN port web server port
Check LAN IP Address	210	None	IVR will announce the IP address of the LAN port
Check WAN Internet Connection Type	100	None	IVR will announce the WAN Internet Connection Type
Set WAN Internet Connection Type (see "Wan Setup" -> "Internet Connection Settings")	101	Enter 0 to use DHCP Enter 1 to use Static IP Enter 3 to use PPPoE	Requires Password
Set Static IP address (WAN Port)	111	Enter IP address using numbers on the telephone keypad. Use the * (star) key when enter a decimal point	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set WAN Network Mask	121	Enter network mask using numbers on the telephone keypad. Use the * (star) key when enter a decimal point	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set WAN Gateway	131	Enter IP address using numbers on the telephone keypad. Use the * (star) key when entering a decimal point.	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set Primary DNS Server IP Address	161	Enter IP address using numbers on the telephone keypad. Use the * (star) key when entering a decimal point.	Requires Password.
		Press 0 to select the router/NAT mode.	If the Voice Gateway acts as the router for your network, use the

참고:관리자 비밀번호가 설정되지 않았거나 사용자가 비밀번호를 변경할 수 있는 경우 비밀번호 필요로 표시된 항목은 비밀번호가 필요하지 않습니다.