

訪問SPA3102互動式語音響應(IVR)選單

目標

互動式語音應答提供裝置內不同配置的說明。當電話連線到裝置時，會獲得這些說明。本文檔加深了對SPA3102互動式語音應答(IVR)選單的理解。

適用裝置

- SPA8000
- SPA3102
- SPA9000
- SPA2102
- SPA112
- PAP2T

軟體版本

- v6.1.12

互動式語音響應(IVR)選單

訪問互動式語音應答選單

步驟1.使用連線到語音網關的PHONE埠的電話。互動式語音應答選單只能通過模擬電話訪問。

步驟2.按四個星號(*)鍵。

步驟3.等到聽到語音提示後顯示「Linksys configuration menu (Linksys配置選單)」。請輸入選項，後跟# (磅) 鍵，或掛斷退出」。

步驟4.請參閱下表列出操作、命令、選單選項和說明。選擇選項後，按# (磅) 鍵。要退出選單，請掛斷電話。

互動式語音應答選單

IVR Action	IVR Menu	Parameter(s)	Notes
Activate IVR Menu	****	None	Ignore SIT or other tones until you hear, "Sipura configuration menu. Please enter option followed by the pound key or hang-up to exit."
Check WAN IP Address	110	None	IVR will announce the IP address of the WAN port
Check WAN Network Mask	120	None	IVR will announce the network mask of the WAN port
Check WAN Gateway	130	None	IVR will announce the gateway of the WAN port
Check MAC Address	140	None	IVR will announce MAC address of the SPA-2100
Check Firmware Version	150	None	IVR will announce the firmware version running on SPA-2100
Check Primary DNS Server IP Address	160	None	IVR will announce the primary DNS server IP address
Check WAN Port Web Server Port	170	None	IVR will announce the WAN port web server port
Check LAN IP Address	210	None	IVR will announce the IP address of the LAN port
Check WAN Internet Connection Type	100	None	IVR will announce the WAN Internet Connection Type
Set WAN Internet Connection Type (see "Wan Setup" -> "Internet Connection Settings")	101	Enter 0 to use DHCP Enter 1 to use Static IP Enter 3 to use PPPoE	Requires Password
Set Static IP address (WAN Port)	111	Enter IP address using numbers on the telephone keypad. Use the * (star) key when enter a decimal point	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set WAN Network Mask	121	Enter network mask using numbers on the telephone keypad. Use the * (star) key when enter a decimal point	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set WAN Gateway	131	Enter IP address using numbers on the telephone keypad. Use the * (star) key when entering a decimal point.	WAN Internet Connection Type must be set to "Static IP", otherwise you will hear "Invalid Option" when you try to use this option. Requires Password.
Set Primary DNS Server IP Address	161	Enter IP address using numbers on the telephone keypad. Use the * (star) key when entering a decimal point.	Requires Password.
		Press 0 to select the router/NAT mode.	If the Voice Gateway acts as the router for your network, use the

附註：如果未設定管理員密碼或允許使用者更改密碼，則標籤為*Requires Password*的專案不需要密碼。