


UCS Central عم UCS لاجم ليجست نم دكأت 1 ةوطخل

ةمولعم ريثك ل دشرم أدبي لصحي يزكرم ل cisco UCS ل تيأر



ةيساسألا ةينبلل ةتباتلل جماربلل جهنللا ل ح نييعت نم دكأت ، ليجستللا ءانثأ 2 ةوطخل
لماش هنأ لىلع سرهفللاو

UCS Central نم ةسايسلا ل ح

Domain to UCS Central Register



Basic

Policy
Resolution
Control

Policy Resolution

Infrastructure & Catalog Firmware	Local	Global
Time Zone Management	Local	Global
Communication Services	Local	Global
Global Fault Policy	Local	Global
User Management	Local	Global
DNS Management	Local	Global
Backup & Export Policies	Local	Global
Monitoring	Local	Global
SEL Policy	Local	Global
Power Allocation Policy	Local	Global
Power Policy	Local	Global
Equipment Policy	Local	Global

Infrastructure & Catalog Firmware

Determines whether the Capability Catalog and infrastructure firmware policy are defined in UCS Manager or in UCS Central

Cancel

Register

UCS ري دم نم جهنلا ل ح

UCS Central

Providers

FSM

Faults

Actions

Register With UCS Central
Unregister From UCS Central

Status

Repair State : **Done**
Registration Status : **Registered**
Cleanup Mode : Localize Global Deep Remove Global
Suspend State :
Acknowledge State :

Properties

Hostname/IP Address : **172.16.16.190**

Policy Resolution Control

Infrastructure & Catalog Firmware : Local Global Determines whether the Capability Catalog and infrastructure firmware policy are defined locally or come from Cisco UCS Central.

Time Zone Management : Local Global Determines whether the time zone and NTP server settings are defined locally or comes from Cisco UCS Central.


Communication Services : Local Global Determines whether HTTP, CIM XML, Telnet, SNMP, web session limits, and Management Interfaces Monitoring Policy settings are defined locally or in Cisco UCS Central.

Global Fault Policy : Local Global Determines whether the Global Fault Policy is defined locally or in Cisco UCS Central.


User Management : Local Global Determines whether authentication and native domains, LDAP, RADIUS, TACACS+, trusted points, locales, and user roles are defined locally or in Cisco UCS Central.

DNS Management : Local Global Determines whether DNS servers are defined locally or in Cisco UCS Central.


روصللا ةبتكم نم ةبسانملا ةيساسأللا ةينبلل تباثلا جم انربلا ةروص لي زنت 3 ةوطخلا



تباثلا جماربلا ةمزح داريتسا راياخ مادختساب ايودي هليزنت نكمي



يف مدختسمل دامتعا تانايب نييعت ةلاح يف Cisco.com نم ةرشابم ةروصلا ليزنت نكمي
باسح Cisco.com.



ةنايصللا ةومجم ةمالع ءاشن 4 ةوطخلا.

لاجم ةومجم لكلا ةنايصللا ةومجم ةمالع قيبطت نكمي

Maintenance Group Tag Create

Domains must be tagged with a Maintenance Group tag to schedule an infrastructure firmware update. When you create a Maintenance Group tag in this dialog, all selected domains are tagged with it.

Maintenance Group Tag Value *

Tag

Select how to apply tags to Domains

By Domain Group Manually

The Maintenance Group tag applies to all existing domains within the Domain Group. It will not be applicable to any new domains that get added further to the domain group. If you select to include sub-domain groups, the Maintenance Group tag also applies to all sub-domain groups.

Domain Group

NA-6200

Include all Sub-Domain Groups

Cancel

Create

يهدف لكشبه لاجملا لى ق بطنس . لاجم لكك لى صلا ة ومجم ة مالع قى ببط نكمي

Maintenance Group Tag Create

Domains must be tagged with a Maintenance Group tag to schedule an infrastructure firmware update. When you create a Maintenance Group tag in this dialog, all selected domains are tagged with it.

Maintenance Group Tag Value *

Tag

Select how to apply tags to Domains

By Domain Group Manually



Filters

Domain Group

- Ungrouped
- root

Platform

- UCS 6100/6200 Series FI
- UCS Mini 6300 Series FI
- UCS 6300 Series FI


Domain	Hardware	Configuration	Status
<input checked="" type="checkbox"/> ANF-UCSPR06 root 172.16.16.153	UCS-FI-6248UP Fabric A, B (HA) 1 Chassis 0 FEX 3 Blades 0 Rack Mounts	UCS 6100/6200 Series FI 3.1(3a)A 3.1(3)SP0(Default) FW Set Startup	OK Fault Level: Major

Cancel


Create

زييمت ة مالع عون لى عوتحت اهؤاشن مت يتلا ة مالعلا تناك اذا امم ققحتلا كنكمي
تامالعلا ةرادا نمض ةناي ص ة ومجم ك


Impacted domains




Firmware status



Impacted domains



Firmware status



Impacted Domains

ةي قرتلا عدبل قلع عمل رارقإلا ةلاحب رارقإلا كنكمي ،ةقل عمل ةطشنألا نمض 7 ةوطخلا

The screenshot shows the 'Pending Activities' page in UCS Central. The page has a search bar at the top and a navigation menu on the left. The main content area displays a table with the following data:

Domain Group	Name	Configuration	Type	Schedule	Status	Pending Changes
<input type="checkbox"/> Ungrouped	ANF-UCSPR06 root	N/A	Infra FW Update	Maintenance Group Scheduler tag	Pending Acknowledgement	Acknowledge

ةمچرتل هذه ل و ح

ةلأل تاي نقتل ن م ة و مچ م ادخت ساب دن تسم ل ا ذه Cisco ت مچرت
م ل ا ل اء ان ا ع مچ ي ف ن م دخت س م ل ل م عد و ت ح م م ي دقت ل ة ي ر ش ب ل و
امك ة ق ي ق د ن و ك ت ن ل ة ي ل ا ة مچرت ل ض ف ا ن ا ة ظ ح ال م ي ج ر ي . ة ص ا خ ل ا م ه ت غ ل ب
Cisco ي ل خ ت . ف ر ت ح م مچرت م ا ه م د ق ي ي ت ل ا ة ي ف ا ر ت ح ال ا ة مچرت ل ا ع م ل ا ح ل ا و ه
ي ل ا م اء ا د ع و ج ر ل ا ب ي ص و ت و ت ا مچرت ل ا هذه ة ق د ن ع ا ه ت ي ل و ئ س م Cisco
Systems (ر ف و ت م ط ب ا ر ل ا) ي ل ص ا ل ا ي ز ي ل ج ن ا ل ا دن ت س م ل ا