

فاشك ت ساو UCS ل يزك رمل ليج ستلا اه حال ص او عا ط خ ال ا

تا يوت حمل ا

[ةم دق م ل ا](#)

[ةم دخت س م ل ا ت ا ن و ك م ل ا](#)

[ا ر ج ال ا](#)

[ا ه ح ال ص او ة ع ئ ا ش ل ا ل ل ي ج س ت ل ا ع ا ط خ ا ف ا ش ك ت س ا](#)

[UCS Central ن م ل ا ج م ل ا ل ل ي ج س ت د ن ع ة ئ ط ا خ UCS ل ا ج م ل ل و ؤ س م ل ا ر و م ة م ل ك : 1 و ي ر ا ن ي س ل ا](#)

[UCS ل ا ج م ت ق و و ي ز ك ر م ل ا UCS ت ق و ة ن م ا ز م م ت م ل : 2 و ي ر ا ن ي س ل ا](#)

[UCS ل ا ج م ن م ل ل ي ج س ت ل ا ا ن ث ا ئ ط ا خ ك ر ت ش م ر س ل ا خ د ا م ت ي : 3 و ي ر ا ن ي س ل ا](#)

[ل ل ي ج س ت ل ا ا ن ث ا UCS ر ي د م ب ل ا ص ت ال ا UCS Central ل ع ر ذ ع ت ي : 4 و ي ر ا ن ي س ل ا](#)

ةم دق م ل ا

UCS عم UCS تالاجم - Cisco نم ةدحوملا ةبسوحلا ماظن ليجست تاوطخ دننتسملا اذه فصوي رادصإلا . طقف UCS ري دم نم ليجستلا اراج نكمي ، UCS 1.5 نم يزك رمل رادصإلا لبق . Central UCS Manager و UCS Central نم لك نم ليجستلا اراج نكمي ، هذعب امو 1.5

ةم دخت س م ل ا ت ا ن و ك م ل ا

UCS 2.0(1a) زارطال يزك رمل ل ا

UCS 3.1(3a) ري دم

ةي لم عم ةزهجأ يه ةم دخت س م ل ا ةزهجأ ل ا ع ي ج

ا ر ج ال ا

UCS ل ا ج م ن م ل ل ي ج س ت ل ا ة ي ل م ع :

Admin-> Communication Management-> UCS Central ل ع ر ق ن ا و CatUCS Manager ج م ا ن ر ب ل

UCS Central م ا د خ ت س ا ب ل ل ي ج س ت ل ا د د ح .

ليجستل ةسرامم لضفأ امئاد) UCS Central ل كرتشملا رسلاو IP ناوع / فيضملا مسا لخدأ DNS، لخدأ مادختساب IP ناوع ريغت نكمي شيح، فيضملا مسا مادختساب UCS Central، ليجستل ءدبل قفاوم ىلع رقناو (لجمل ليجست متي امنيب

دعب هريغت نكمي امك . ليجستل ءانثأ جهنلا ليجست في مكحتل رصنع نيغت نكمي ليجستل.

Register With UCS Central



Hostname/IP Address :

Shared Secret :

All Global

Policy Resolution Control

Infrastructure & Catalog Firmware : Local Global

Determines whether the Capability Catalog and infrastructure firmware policy are defined locally or come from Cisco UCS Central.

Time Zone Management : Local Global

Determines whether the time zone and NTP server settings are defined locally or comes from Cisco UCS Central.

Communication Services : Local Global

Determines whether HTTP, CIM XML, Telnet, SNMP, web session limits, and Management Interfaces Monitoring Policy settings are defined locally or in Cisco UCS Central.

Global Fault Policy : Local Global

Determines whether the Global Fault Policy is defined locally or in Cisco UCS Central.

User Management : Local Global

Determines whether authentication and native domains, LDAP, RADIUS, TACACS+, trusted points, locales, and user roles are defined locally or in Cisco UCS Central.

DNS Management : Local Global

Determines whether DNS servers are defined locally or in Cisco UCS Central.

OK

Cancel

Register With UCS Central



Hostname/IP Address :

Shared Secret :

All Global

Policy Resolution Control

- Infrastructure & Catalog Firmware : Local Global
Determines whether the Capability Catalog and infrastructure firmware policy are defined locally or come from Cisco UCS Central.
- Time Zone Management : Local Global
Determines whether the time zone and NTP server settings are defined locally or comes from Cisco UCS Central.
- Communication Services : Local Global
Determines whether HTTP, CIM XML, Telnet, SNMP, web session limits, and Management Interfaces Monitoring Policy settings are defined locally or in Cisco UCS Central.
- Global Fault Policy : Local Global
Determines whether the Global Fault Policy is defined locally or in Cisco UCS Central.
- User Management : Local Global
Determines whether authentication and native domains, LDAP, RADIUS, TACACS+, trusted points, locales, and user roles are defined locally or in Cisco UCS Central.
- DNS Management : Local Global
Determines whether DNS servers are defined locally or in Cisco UCS Central.

OK

Cancel

ليجستال ةيلمع نم ققحتلل (ةدودحمل ةلاحل زاهج) FSM ةلاح ةبقارب مق

All / Communication Management / UCS Central

UCS Central Providers FSM Faults

UCS Central Registration Policy Resolution Control

FSM Status : **Success**

Description :

Current FSM Name : **Register Fsm**

Completed at : **2017-08-18T13:02:42Z**

Progress Status :

Remote Invocation Result : **Not Applicable**

Remote Invocation Error Code : **None**


Remote Invocation Description :

Step Sequence


Order	Name	Description	Status	Timestamp	Retried
1	Register Fsm Execute	Register FSM Execute(FS...	Success	2017-08-18T13:02:42Z	2

UCS Central نم ليجستال ةيلمع

لاحمل ةرادى لى لقتناو ماظنللا تاودأ قوف رقناو UCS Central ليغشتب مق



ىنمىلا ةيوازلا ي ف لاجم لىجست قوف رقنا .



مسا ددح . ةملاك و مسا لمعتسم لوؤسملا و ناوع hostname/IP لاجم UCS لال تلخد لىض ف اريغت امئاد نكمي . لىجست لال لىل ع رقنا و UCS Central ب صاخ لال IP ناوع/ فىضم لال DNS، لال ادخ ت سا ب IP ناوع فىضم لال مسا مادخت سا ب يزك رمل UCS لىجست ل ةس رامم ب (لال لىجست متي امنى ب).

Domain to UCS Central Register



Policy
Resolution
Control

UCS Central System Profile - Date & Time

In addition, if HTTPS is supported on the Domain, it must be enabled in order to register with UCS Central.

UCS Domain Hostname/IP Address *

ucsdomain.cisco.com

UCS Domain User Name *

admin

UCS Domain Password

Registration Hostname/IP address from UCS Central

hk-central-2

Cisco best practice is to register UCS Domains to UCS Central using the Fully Qualified Domain Name (FQDN). If you register the UCS Domain to UCS Central using an IP address and later change the IP address of UCS Central, you will need to unregister and re-register the UCS Domain to UCS Central.

[UCS Central System Profile - DNS](#)

Cancel

Register

نېوكتلا ةلاح بېوېتلا ةمالة نم FSM ةلاح ةبقارم نكمي.

Register Domain

Filter Export Delete Unregister Domain

<input type="checkbox"/>	UCS Domain	Timestamp	Registration Status	Q
<input type="checkbox"/>	172.16.16.153	17-Aug-2017 3:42:05 PM	In Progress Configuration Status	

اهالصالو ةعئاشلا ليجستلا ءاطخأ فاشكتسا:

UCS نم لاجملا ليجست دنه ةئاطخ UCS لاجملا لوؤسملا رورم ةملك: 1 ويرانيسلا Central.

ىرخأ ةرم ليجستلا لواحو لوؤسملا رورم ةملك حيصت ب مق: حالصالا

UCS Central نم FSM ةلاح

Domain Registrations Configuration Status

System FSM Name Registration Fail	Status Registration Fail	Progress Status <div style="width: 10%;"><div style="width: 10%;"></div></div> 10%	FSM Details		
Current Stage Name Authorizing Admin Credentials	Stage Status Failed	Retries 1	Time Stamp 17-Aug-2017 3:40:54 PM		
Order	Name	Description	Timestamp	Retries	Status
3	Remote Domain Reg Check Status			0	Skipped
2	Remote Domain Reg Push Shared Secret			0	Skipped
1	Authorizing Admin Credentials	Authorizing the admin credentials against the remote domain(FSM-STAGE:sam:dme:PolicyControlEpOpRemoteDomainReg:Registration)	17-Aug-2017 3:40:54 PM	1	Failed

Close

لاجمو يزكرم ل UCS تي قوت ةنمازم مت مل 2: ويراني ل UCS.

سرخ ةرم ةلكي هلا عارج لواح م UCS لاجم و UCS Central لىل ع تقولا ةنمازم ب مق: حالصالا

تقولا حي صتل هاندا طابترالاي ف UCS ةرادا ي ف يرابجالا تقولا ةنمازم لىل ع جرا

https://www.cisco.com/c/en/us/td/docs/unified_computing/ucs/ucs-central/GUI-User-Guides/Operations/b_UCSC_Ops_Guide_2_0/b_UCSC_Ops_Guide_2_0_chapter_01100.html

UCS ري دم نم FSM ةلا ح

FSM Status : **In Progress**
 Description :
 Current FSM Name : **Repair Cert**
 Completed at :
 Progress Status :
 Remote Invocation Result : **Resource Unavailable**
 Remote Invocation Error Code : **5**
 Remote Invocation Description : **UCSM and UCS Central time is not synchronized. Retrying...**

⊖ Step Sequence

Order	Name	Description	Status	Timestamp	Retried
1	Repair Cert Verify Guid	verifying GUID of UCS Ce...	In Progress	2017-08-17T22:41:53Z	1
2	Repair Cert Unregister		Pending		0
3	Repair Cert Clean Old Data		Pending		0
4	Repair Cert Request		Pending		0
5	Repair Cert Verify		Pending		0

ليجستلا اناثا ئطاخ كرتشم رس لاخدا متي: 3 ويرانيسيلا UCS لاچم نم

ىرخا ةرم خس نلا اءرجا لواو وحيصلا كرتشم لا رسلا لاخدا: حالصلا

"كرتشم لا رسلا" ريغتلا هاندا طابترالا ي ف "كرتشم لا رسلا" نييعت ةءاعلا لىلا عجرا

https://www.cisco.com/c/en/us/td/docs/unified_computing/ucs/ucs-central/install-upgrade/2-0/b_Cisco_UCSC_Install_and_Upgrade_Guide_2_0/b_Cisco_UCSC_Install_and_Upgrade_Guide_2_0_chapter_0101.html#task_8299DFA4853049068C7E384F5E8FF493

UCS ريديم نم FSM ةلاچ

UCS Central Providers **FSM** Faults

UCS Central Registration Policy Resolution Control

FSM Status : **Fail**

Description :

Current FSM Name : **Repair Cert**

Completed at : **2017-08-17T22:45:38Z**

Progress Status :

Remote Invocation Result : **Failure**

Remote Invocation Error Code : **5**

Remote Invocation Description : **shared secret mismatch**

⊖ Step Sequence

Order	Name	Description	Status	Timestamp	Retried
1	Repair Cert Verify Guid	verifying GUID of UCS Ce...	In Progress	2017-08-17T22:43:10Z	2
2	Repair Cert Unregister		Pending		0
3	Repair Cert Clean Old Data		Pending		0
4	Repair Cert Request		Pending		0
5	Repair Cert Verify		Pending		0

UCS ري دم ب لاصت ال UCS Central ى لى رذعتي : 4 وي راني س ل ليج ست ل انا ث أ

443 ى لى UCS Central و UCSM ن ب لاصت ال ع نمي ة ي ام ح راج دوج و مدع نم دكأت : حال ص ال

UCS ري دم نم FSM ة لاج

UCS Central Providers **FSM** Faults

UCS Central Registration Policy Resolution Control

FSM Status : **In Progress**

Description :

Current FSM Name : **Repair Cert**

Completed at :

Progress Status :

Remote Invocation Result : **Not Applicable**

Remote Invocation Error Code : **None**

Remote Invocation Description :

⊖ Step Sequence

Order	Name	Description	Status	Timestamp	Retried
1	Repair Cert Verify Guid	verifying GUID of UCS Ce...	In Progress	2017-08-17T22:49:34Z	1
2	Repair Cert Unregister		Pending		0
3	Repair Cert Clean Old Data		Pending		0
4	Repair Cert Request		Pending		0
5	Repair Cert Verify		Pending		0

Save Changes Revert Values

ةمچرتل هذه لوج

ةللأل تاي نقتل نمة ومة مادختساب دن تسمل اذة Cisco تمةرت
ملاعلاء انء مء مء نمة دختسمل معد و تمة مء دقتل ةر شبل او
امك ةق قء نوك ت نل ةللأل ةمچرت لصف أن ةظحال مء ءرء. ةصاأل مء تءل ب
Cisco ةللخت. فرتمة مچرت مء مء دقء ةللأل ةل فارتحال ةمچرتل عم لاعل او
ىل إلمءءاد ءوچرلاب ةصوء و تاملرتل هذه ةقء نء اهءل وئس م Cisco
Systems (رفوتم طبارل) ةلصلأل ةزىل ءنل اءل دن تسمل