



Release Notes for Cisco Wireless Control System Navigator 1.5.181.0

February 2010

These release notes describe open and resolved caveats for the Cisco Wireless Control System Navigator maintenance release 1.5.181.0.

The Cisco Wireless Control System Navigator is referred to as the *Cisco WCS Navigator*.

Contents

These release notes contain the following sections:

- [Introduction, page 2](#)
- [Cisco WCS Navigator Features, page 2](#)
- [Requirements for Cisco WCS Navigator, page 2](#)
- [Important Notes, page 4](#)
- [Caveats, page 5](#)
- [Troubleshooting, page 6](#)
- [Related Documentation, page 6](#)
- [Obtaining Documentation and Submitting a Service Request, page 6](#)



Americas Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

© 2010 Cisco Systems, Inc. All rights reserved.

Introduction

The Cisco WCS Navigator manages multiple Cisco WCSs (running the same release as Navigator) and provides a unified view of the network. It uses SOAP/XML over HTTPs to communicate with individual WCSs. Navigator provides monitoring functionality and reporting capability across all WCSs. In addition, network-wide searches are available. In Windows and Linux, Cisco WCS Navigator runs as a service continuously and resumes running after a reboot.

Cisco WCS Navigator delivers an aggregated platform for enhanced scalability, manageability, and visibility of large-scale implementations of the Cisco Unified Wireless Network. This software-based solution gives network administrators easy access to information from multiple geographically diverse Cisco WCS management platforms. It supports partitioning of the unified wireless network at the management level.

Cisco WCS Navigator Features

The Cisco WCS Navigator provides:

- Management of multiple Cisco WCSs
 - Supports up to 20 Cisco WCS management platforms
 - Management of up to 30,000 Cisco Aironet lightweight access points from a single management console
- A unified view of the network
- Overview and multilevel monitoring of wireless networks
- The ability to run reports for all WCSs
- Network-wide searches
- A link to return to the Navigator when directed to a regional WCS from Navigator

Requirements for Cisco WCS Navigator

Hardware Requirements for Navigator

The following server hardware and software is required to support Cisco WCS Navigator for Windows or Linux.

- Supports up to 20 wireless control systems depending on the Navigator license.
- A 3.2 GHz Intel Dual Core processor with 4 GB of RAM and an 80-GB hard drive.
- A 40-GB minimum of available disk space on your hard drive.

**Note**

For all server levels, AMD processors equivalent to the listed Intel processors are also supported.



Note The available disk space listed is a minimum requirement but may be different for your system depending on the number of backups.



Note The recommended screen resolution is 1024 x 768 pixels for Navigator.

Client Requirements

The Cisco Navigator user interface requires Internet Explorer 7.0 with the Flash plugin or Mozilla Firefox 3 or later. The Cisco Navigator user interface has been tested and verified with Internet Explorer and Firefox on a Windows platform.



Note Cisco recommends Mozilla Firefox 3.0 or later for best results.



Note Internet Explorer 6.0 is currently supported, but support will be removed in a future release.

Using a web browser running on Windows 2003 to access the WCS web GUI is not recommended because recommended Windows 2003 security settings may cause browsing problems.

The client running the browser must have a minimum of 1 GB of RAM and a 2-GHz processor. The client device should not be running any CPU or memory-intensive applications.



Note The minimum screen resolution that is recommended for both WCS and Navigator use is 1024 x 768 pixels.

Supported Operating Systems

The following operating systems are supported:

- Windows 2003/SP2 or later with all critical and security Windows updates installed. 64-bit installations are not supported.



Note Windows 2003 32-bit installations provide support for up to 64 GB of RAM provided Physical Address Extension (PAE) is enabled. Refer to Windows documentation for instructions on enabling this mode.

- Red Hat Linux Enterprise Server 5.0, 5.1, and 5.2—Only 32-bit operating system installations are supported.



Note Red Hat Linux Enterprise Server 5.0 or 5.1—64-bit operating system installations are not supported.



Note A 32-bit operating system running on 64-bit capable hardware is supported for both Windows and Linux.

- Windows 2003 and Redhat Linux version support on VMware ESX 3.0.1 version and above.



Note VMware must be installed on a system with these minimum requirements:
 Quad CPU running at 3.16 GHz
 8 GB RAM
 200 GB hard drive



Note Individual operating systems running WCS in VMware must follow the specifications for the size of WCS you intend to use.



Note The Cisco WCS Navigator supports both Internet Explorer 6.0 and 7.0.

Important Notes

WCS and Navigator Compatibility

WCS and Navigator must be from the same release in order to be compatible (see [Table 1](#)). Although the release numbers will not be the same, you must verify whether they were part of the same release.

For example, Navigator 1.0 is compatible with WCS 4.1, and Navigator 1.1.x is compatible with any WCS 4.2.x.



Note When Navigator is upgraded to a newer version, the corresponding WCS must also be upgraded to the corresponding version. For example, if Navigator is upgraded to 1.5, WCS must be upgraded to the corresponding 6.0.

Table 1 *Compatibility Matrix*

Navigator Release Number	WCS Release Number
1.0.83.0	4.1.83.0
1.0.91.0	4.1.91.0, 4.1.83.0
1.1.62.0	4.2.62.0
1.1.62.11	4.2.62.11, 4.2.62.0
1.1.81.0	4.2.81.0, 4.2.62.11, 4.2.62.0
1.1.97.0	4.2.97.0, 4.2.81.0, 4.2.62.11, 4.2.62.0
1.1.110.0	4.2.97.0, 4.2.81.0, 4.2.62.11, 4.2.62.0, 4.2.110.0
1.1.128.0	4.2.97.0, 4.2.81.0, 4.2.62.11, 4.2.62.0, 4.2.110.0, 4.2.128.0

Table 1 **Compatibility Matrix (continued)**

Navigator Release Number	WCS Release Number
1.3.64.0	5.1.64.0
1.4.110.0	5.2.110.0
1.4.130.0	5.2.130.0, 5.2.110.0
1.4.148.0	5.2.148.0
1.5.132.0	6.0.132.0
1.5.170.0	6.0.132.0 and later
1.5.181.0	6.0.132.0 and later

Japanese Microsoft Windows Support

This release adds support for the use of Cisco WCS Navigator on a server running the Japanese version of Microsoft Windows. Cisco Navigator will run in English.

Flash Player Software Version 9.0.115.0

Flash Player software 9.0.115.0 is required for the full WCS benefit.

Caveats

This following sections lists [Open Caveats](#) and [Resolved Caveats](#) for this software release. For your convenience in locating caveats in Cisco's Bug Toolkit, the caveat titles listed in this section are taken directly from the Bug Toolkit database. These caveat titles are not intended to be read as complete sentences because the title field length is limited. In the caveat titles, some truncation of wording or punctuation might be necessary to provide the most complete and concise description. The only modifications made to these titles are as follows:

- Commands are in **boldface** type.
- Product names and acronyms may be standardized.
- Spelling errors and typos may be corrected.



Note

If you are a registered cisco.com user, view Bug Toolkit on cisco.com at the following website:

<http://tools.cisco.com/Support/BugToolKit/>

To become a registered cisco.com user, go to the following website:

<http://tools.cisco.com/RPF/register/register.do>

Open Caveats

There are no open caveats in this release.

Resolved Caveats

There are no resolved caveats in this release.

If You Need More Information

If you need information about a specific caveat that does not appear in these release notes, you can use the Cisco Bug Toolkit to find caveats of any severity. Click this URL to browse to the Bug Toolkit:

<http://tools.cisco.com/Support/BugToolKit/>

(If you request a defect that cannot be displayed, the defect number might not exist, the defect might not yet have a customer-visible description, or the defect might be marked Cisco Confidential.)

Troubleshooting

For the most up-to-date, detailed troubleshooting information, refer to the Cisco TAC website at the following location:

<http://www.cisco.com/tac>

Click **Technology Support**, select **Wireless** from the menu on the left, and click **Wireless LAN**.

Related Documentation

For information on the Cisco WCS Navigator, refer to the *Cisco Wireless Control System Navigator 1.1.62 Installation Guide*.

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS Version 2.0.

CCDE, CCENT, CCSI, Cisco Eos, Cisco HealthPresence, Cisco IronPort, the Cisco logo, Cisco Nurse Connect, Cisco Pulse, Cisco SensorBase, Cisco StackPower, Cisco StadiumVision, Cisco TelePresence, Cisco Unified Computing System, Cisco WebEx, DCE, Flip Channels, Flip for Good, Flip Mino, Flipshare (Design), Flip Ultra, Flip Video, Flip Video (Design), Instant Broadband, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn, Cisco Capital, Cisco Capital (Design), Cisco:Financed (Stylized), Cisco Store, Flip Gift Card, and One Million Acts of Green are service marks; and Access Registrar, Aironet, AllTouch, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Lumin, Cisco Nexus, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, Continuum, EtherFast, EtherSwitch, Event Center, Explorer, Follow Me Browsing, GainMaker, iLynX, IOS, iPhone, IronPort, the IronPort logo, Laser Link, LightStream, Linksys, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, PCNow, PIX, PowerKEY, PowerPanels, PowerTV, PowerTV (Design), PowerVu, Prisma, ProConnect, ROSA, SenderBase, SMARTnet, Spectrum Expert, StackWise, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0910R)