

Resolución de Problemas de Análisis de Flujo de Llamadas CVP con Servidor VVB

Contenido

[Introducción](#)

[Prerequisites](#)

[Requirements](#)

[Componentes Utilizados](#)

[Antecedentes](#)

[CVP con análisis de seguimiento de flujo de llamada VVB](#)

[Información Relacionada](#)

Introducción

Este documento describe el análisis de seguimiento de Cisco Customer Voice Portal (CVP) con Cisco Virtual Voice Browser (VB) como un navegador VXML.

Prerequisites

Requirements

Cisco recomienda que tenga conocimiento sobre estos temas:

- CVP con Cisco Unified Contact Center Enterprise (UCCE)
- Cisco VVB integrado con CVP
- Flujo de llamadas completo de CVP

Componentes Utilizados

La información que contiene este documento se basa en las siguientes versiones de software y hardware.

- CVP 11.5
- UCCE 11.5
- VVB 11.5

The information in this document was created from the devices in a specific lab environment. All of the devices used in this document started with a cleared (default) configuration. Si tiene una red en vivo, asegúrese de entender el posible impacto de cualquier comando.

Antecedentes

Con la introducción de Cisco VVB como navegador VXML, aquí hay un análisis de seguimiento de ejemplo para rastrear las señales entre CVP, UCCE y VVB.

En este análisis, la llamada se enruta al CVP y, después del tratamiento de respuesta de voz interactiva (IVR), el CVP enruta la llamada a un agente disponible.

Las palabras clave MIVR y CVP pueden identificar los fragmentos de registro CVP y VVB en los seguimientos.

CVP con análisis de seguimiento de flujo de llamada VVB

Nuevo indicador luminoso de switch de llamada

```
1937: 192.0.2.11: May 10 2017 11:39:37.880 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=DATAI.1} NEW CALL
with guid=0F46E580000100000000007A0851430A legid=56A1AA52-345511E7-ABF1C227-5C85A942 dn=9876
ani=12345 uui=null calldate=Wed May 10 11:39:37 EST 2017 video=false cachecallcontext = false
is_postcallsurvey = false RouterCallKey = null RouterCallKeyDay = null
RouterCallKeySequenceNumber = null
```

Número de sesiones activas

```
44241: 192.0.2.11: May 10 2017 11:39:37.880 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Core-router-
group-0} --NEW SESSION CREATED--CALLGUID=0F46E580000100000000007A0851430A NUMBER OF ACTIVE
SESSIONS= 1
```

Nueva llamada en SIP SS

```
4281: 192.0.2.11: May 10 2017 11:39:37.880 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-
group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] -
Processing from SIP_SS - [NEW_CALL] DialogID=0 SendSeqNo=0 DNIS=9876 ANI=12345 CED= rckey=0
rcday=0 rcseq=0 uui= callguid=0F46E580000100000000007A0851430A trunkGroupId=0 trunkNumber=0
serviceId=0 calledNumber= location= locationpkid= pstntrunkgroupid= sipheader= ECC variables=
ECC arrays= Peripheral Variables=
```

Nueva llamada: publicación en UCCE

```
4282: 192.0.2.11: May 10 2017 11:39:37.880 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-
group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] -
Publishing to UCCE - [NEW_CALL] DialogID=46 SendSeqNo=1 DNIS=9876 ANI=12345 CED= rckey=0 rcday=0
rcseq=0 uui= callguid=0F46E580000100000000007A0851430A trunkGroupId=100 trunkNumber=0
serviceId=1 calledNumber= location= locationpkid= pstntrunkgroupid= sipheader= ECC
variables=user.media.id: 0F46E580000100000000007A0851430A, ECC arrays= Peripheral Variables=
```

Conectividad temporal: procesamiento desde UCCE

```
4283: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-
group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] -
Processing from UCCE - ,, [ICM_TEMPORARY_CONNECT], rckey=201, rcday=152070, DNIS=9876, ANI=12345
```

Conexión temporal: publicación en sip SS

```
4284: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-
group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] -
Publishing to SIP_SS - [CONNECT] DialogID=46 SendSeqNo=0 Label=8888111111 TxrHint=false
rckey=152070 rcdays=152070 rcseq=0 location= locationpkid= sipheader= uui= whisperAnnounce=null
callguid=0F46E580000100000000007A0851430A ECC variables=user.media.id:
0F46E580000100000000007A0851430A,user.microapp.app_media_lib: ..,user.microapp.media_server:
http://192.0.2.11:7000/CVP,user.microapp.UseVXMLParams: N, ECC
arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143,
Peripheral Variables=
```

Coincidencia de ruta para etiqueta VRU

```
1941: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-120-
SIP-19461} Static route matched 88881111112 to StaticRoute: patterns like 88881111> will route
to 192.0.2.12
1942: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-120-
SIP-19461} Using Local Static Route for sip:88881111112@192.0.2.12
```

Invitación a la plataforma VXML GW-VRU

```
1947: 192.0.2.11: May 10 2017 11:39:37.896 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-120-
SIP-19461} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-
149438037789633 - [OUTBOUND]: INVITE TO <sip:88881111112@192.0.2.12;transport=tcp> FROM "PSTN
PHONE--CVP_11_5_1_0_1_0_344" <sip:12345@192.0.2.11:5060> EXPIRES[60] 100REL[Unsupported]
```

Nueva llamada al indicador luminoso VVB VRU

```
195208: May 10 11:21:27.305 AEST %MIVR-JASMIN-7-UNK:[CALLID=0F46E580000100000000007A0851430A-
149438037789633] NEW_CALL, GUCID=0F46E580000100000000007A0851430A; GUID=0256304512-0000065536-
0000000122-0139543306; CallId=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11;
URI=sip:88881111112@192.0.2.12;transport=tcp
```

```
### CALL_NEW () from VVB to VXML server
```

```
189323: May 02 16:10:49.778 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-
149370661959432] Browser.makeRequest(): got encoded
uri=http://192.0.2.11:7000/CVP/Server?MSG_TYPE=CALL_NEW&CALL_DNIS=8888111111&CALL_ANI=sip%3A6000
6099%40..
.
```

Invitación aceptada - Tramo VRU

```
1951: 192.0.2.11: May 10 2017 11:39:38.067 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=DIALOG_CALLBACK.5}
CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-
149438037789633 - [OUTBOUND]: Invitation accepted - ack'ing
```

Respuesta

```
1958: 192.0.2.11: May 10 2017 11:39:38.083 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-121-
SIP-19462} Sending BUS MSG for Event Reportnew CSS:[EVENT_REPORT] DialogID=0 SendSeqNo=0
EventID=ANSWER CauseCode=CAUSE_NONE
```

Respuesta: procesamiento desde SIP SS

4285: 192.0.2.11: May 10 2017 11:39:38.083 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Processing from SIP_SS - [EVENT_REPORT] DialogID=0 SendSeqNo=0 EventID=ANSWER CauseCode=CAUSE_NONE

Respuesta: publicación en UCCE

4286: 192.0.2.11: May 10 2017 11:39:38.083 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Publishing to UCCE - [EVENT_REPORT] DialogID=46 SendSeqNo=2 EventID=ANSWER CauseCode=NONE

Nueva llamada [IVR]: procesamiento desde VXMLServer - Nueva llamada con VRU + ID de correlación

44242: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A [IVR] - processing from VXMLServer - [NEW_CALL]
ClientNewCallEvent,sessionId=0F46E580000100000000007A0851430A ani=sip:12345@192.0.2.11:5060 dnis=88881111112 uui= callId=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 seqNo=1 invokationId=0 message=null ccbServletUrl= ccbServletReqTimeout=0

Nueva publicación de llamadas a ICM_SS

44243: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 [IVR] [Publishing to ICM_SS] [NEW_CALL] DialogID=0 SendSeqNo=0 DNIS=88881111112 ANI=12345 CED= rckey=0 rcdays=0 rcseq=0 uui= callguid=0F46E580000100000000007A0851430A trunkGroupId=0 trunkNumber=0 serviceId=0 calledNumber= location= locationpkid= pstntrunkgroupid= sipheader= ECC variables= ECC arrays= Peripheral Variables=

ID de correlación de llamada enrutada

4287: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID = 0F46E580000100000000007A0851430A - Correlation ID routed call [IVR-VRU_LEG_DIALOG]-procesado desde IVR_SS-[NEW_call]-VRU Leg Dialog ID

4288: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Processing from IVR_SS - [NEW_CALL] DialogID=0 SendSeqNo=0 DNIS=88881111112 ANI=12345 CED= rckey=0 rcdays=0 rcseq=0 uui= callguid=0F46E580000100000000007A0851430A trunkGroupId=0 trunkNumber=0 serviceId=0 calledNumber= location= locationpkid= pstntrunkgroupid= sipheader= ECC variables= ECC arrays= Peripheral Variables=

[Request_Instruction]: publicación en UCCE

4289: 192.0.2.11: May 10 2017 11:39:38.364 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] -

Publishing to UCCE - [REQUEST_INSTRUCTION] DialogID=47 SendSeqNo=1 ANI=12345 DNIS=888811111112 correlationId=12 trunkGroupId=200 trunkNumber=0 serviceId=2 uui= calledNumber= location= locationpkid= pstntrunkgroupid= pstntrunkgroupchannelnum=0 sipheader=

[RUN_SCRIPT_REQ]-[IVR_VRU_LEG_DIALOG]-procesado desde UCCE

4294: 192.0.2.11: May 10 2017 11:39:47.521 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Processing from UCCE - [RUN_SCRIPT_REQ] DialogID=47 SendSeqNo=2 InvokeID=2 scriptId=GS,Server,V scriptConfiguration= ANI=12345 ced=complete callguid=0F46E580000100000000007A0851430A rckey=201 rcdays=152070 rcseq=1 uui= featureType=0 featureParam1= _featureParam2= ECC variables=user.media.id: 0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib: ..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input: complete,user.microapp.UseVXMLParams: N, ECC arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143, Peripheral Variables=

[RUN_SCRIPT_REQ]-[IVR_VRU_LEG_DIALOG] - Publicar en IVR_SS

4295: 192.0.2.11: May 10 2017 11:39:47.536 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Publishing to IVR_SS - [RUN_SCRIPT_REQ] DialogID=47 SendSeqNo=2 InvokeID=2 scriptId=GS,Server,V scriptConfiguration= ANI=12345 ced=complete callguid=0F46E580000100000000007A0851430A rckey=201 rcdays=152070 rcseq=1 uui= featureType=0 featureParam1= _featureParam2= ECC variables=user.media.id: 0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib: ..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input: complete,user.microapp.UseVXMLParams: N, ECC arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143, Peripheral Variables=

Procesamiento [RUN_SCRIPT_REQ]-[IVR] desde ICM_SS

44250: 192.0.2.11: May 10 2017 11:39:47.536 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 [IVR] [processing from ICM_SS] [RUN_SCRIPT_REQ] DialogID=47 SendSeqNo=2 InvokeID=2 scriptId=GS,Server,V scriptConfiguration= ANI=12345 ced=complete callguid=0F46E580000100000000007A0851430A rckey=201 rcdays=152070 rcseq=1 uui= featureType=0 featureParam1= _featureParam2= ECC variables=user.media.id: 0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib: ..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input: complete,user.microapp.UseVXMLParams: N, ECC arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143, Peripheral Variables=

[RUN_SCRIPT_REQ]-[IVR]- Publicar en servidor VXML

44251: 192.0.2.11: May 10 2017 11:39:47.536 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 [IVR] - Publishing to VXMLServer - [RUN_SCRIPT_REQ] DialogID=47 SendSeqNo=2 InvokeID=2 scriptId=GS,Server,V scriptConfiguration= ANI=12345 ced=complete callguid=0F46E580000100000000007A0851430A rckey=201 rcdays=152070 rcseq=1 uui= featureType=0 featureParam1= _featureParam2= ECC variables=user.media.id: 0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib: ..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input: complete,user.microapp.UseVXMLParams: N, ECC

arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143,
Peripheral Variables=

VVB AUDIUM_Root(AUDIUM_VXML)

178107: May 02 16:07:47.410 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] application (Root document):
/CVP/Server?audium_root=true&calling_into=HelloWorld

Documento RAÍZ VVB

178424: May 02 16:07:56.480 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] VoiceBrowser.invokeRootDocument:
[URI=http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld fragment=null]

VVB loadbAndParse

178430: May 02 16:07:56.481 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] VXMLDocumnet.loadbAndParse(): fetching
(http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld) timeout attribute=0

solicitud de realización del buscador VVB

178435: May 02 16:07:56.481 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Browser.makeRequest(): got encoded
uri=http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld

VVB Fetch VXML doc

178444: May 02 16:07:56.489 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Browser.fetchVxml(): got doc from new VxmlDocStream(type: 1, cnt:
com.cisco.wf.cache.http.CachedURLConnection:http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld, cachable: true, isFromCache: false, lastModified: 0)

###VVB successfully fetched

178445: May 02 16:07:56.489 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Successfully fetched bytes: 0, duration(s): 0.008, URI:
http://192.0.2.11:7000/CVP/Server?audium_root=true&calling_into=HelloWorld

VXML Content

Content of VXML Document

<?xml version="1.0" encoding="UTF-8"?>

<vxml version="2.0">

.....

POST DE ENVÍO DE VVB ()

178480: May 02 16:07:56.494 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] GotoRequest.handleSubmitElement(): goto req=http://192.0.2.11:7000/CVP/Server

178481: May 02 16:07:56.494 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] GotoRequest.handleSubmitElement(): req's method=post

Resultado de la publicación ENVIAR

178506: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Fetch: HTTP 200 OK
178507: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Browser.fetchVxml(): got doc from new VxmlDocStream(type: 1, cnt: com.cisco.net.www.protocol.http.HttpURLConnection:http://192.0.2.11:7000/CVP/Server, cachable: false, isFromCache: false, lastModified: 0)
178508: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Successfully fetched bytes: 0, duration(s): 0.004, URI: http://192.0.2.11:7000/CVP/Server

Elemento Handle

178603: May 02 16:07:56.509 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] GotoRequest.handleSubmitElement(): goto req=http://192.0.2.11:7000/CVP/Server
178604: May 02 16:07:56.509 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] GotoRequest.handleSubmitElement(): req's method=post

Crea una nueva consulta

178510: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] Content of POST query:
audium_vxmlLog=
178511: May 02 16:07:56.500 AEST %MIVR-SS_VB-7-UNK:Content of VXML Document:
<?xml version="1.0" encoding="UTF-8"?>
<vxml version="2.0" application="/CVP/Server?audium_root=true&calling_into>HelloWorld">
<form id="audium_start_form">
<block>

Resultado de la publicación (carga de audio)

178579: May 02 16:07:56.503 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] <audio> src:/CVP/audio/helloworld_audio.wav expr:
178580: May 02 16:07:56.503 AEST %MIVR-SS_VB-7-UNK:[CALLID=43A31C0000010000000000790851430A-149370359030630] checkWriteOnDiskForVVB: Setting Disk write to true for VVB

[RUN_SCRIPT_RESULT][IVR]- procesamiento desde VXMLServer

44257: 192.0.2.11: May 10 2017 11:39:50.927 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 [IVR] - processing from VXMLServer - [RUN_SCRIPT_RESULT] DialogID=0 SendSeqNo=0 InvokeID=0 Result=1 CED= newTransaction=0 ECC variables= ECC arrays= Peripheral Variables=

[RUN_SCRIPT_RESULT][IVR]-publicación en ICM_SS

44248: 192.0.2.11: May 10 2017 11:39:47.521 +1000: %CVP_11_5_IVR-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A CALLID=0F46E580000100000000007A0851430A-149438037789633@192.0.2.11 [IVR] [Publishing to ICM_SS] [RUN_SCRIPT_RESULT] DialogID=0 SendSeqNo=0 InvokeID=1 Result=1 CED=complete newTransaction=0 ECC variables=user.microapp.error_code: 0,user.microapp.metadata: N|000|01|00|00|009141|GS,Server,V,user.microapp.caller_input: complete, ECC arrays= Peripheral Variables=

[RUN_SCRIPT_RESULT][IVR_VRU_LEG_DIALOG]-Procesamiento desde IVR_SS- Resultado=1

4292: 192.0.2.11: May 10 2017 11:39:47.521 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Processing from IVR_SS - [RUN_SCRIPT_RESULT] DialogID=0 SendSeqNo=0 InvokeID=1 Result=1 CED=complete newTransaction=0 ECC variables=user.microapp.error_code: 0,user.microapp.metadata: N|000|01|00|00|009141|GS,Server,V,user.microapp.caller_input: complete, ECC arrays= Peripheral Variables=

[RUN_SCRIPT_RESULT][IVR_VRU_LEG_DIALOG]-Publicar en UCCE

4293: 192.0.2.11: May 10 2017 11:39:47.521 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Publishing to UCCE - [RUN_SCRIPT_RESULT] DialogID=47 SendSeqNo=2 InvokeID=1 Result=1 CED=complete newTransaction=0 ECC variables=user.microapp.error_code: 0,user.microapp.metadata: N|000|01|00|00|009141|GS,Server,V,user.microapp.caller_input: complete, ECC arrays= Peripheral Variables=

El agente se encuentra disponible y ICM cancela la operación VXML

4296: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} 47CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE]sending ICMEvent, sessionId=0F46E580000100000000007A0851430A callId=null dialogId=47 sourceId=null systemType=ICM mediatype= dnis= ani= srcAddress= locationsiteid=sessionId=0F46E580000100000000007A0851430A callType=0 cacheCallContext=false postcallsurveycall=false icmMessage=DIALOGUE_FAILURE_CONF

[Dialog_failure_conf]-[IVR_VRU_LEG_DIALOG publicar en UCCE]

4297: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Publishing to UCCE - [DIALOGUE_FAILURE_CONF] DialogID=47 SendSeqNo=3 InvokeID=2 ErrorCode=E_OPERATION_CANCELLED

[CANCELAR]-Procesamiento desde UCCE

4298: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] - Processing from UCCE - [CANCEL] DialogId=47 SendSeqNo=3 InvokeID=3 ReqID=2

[Connect] procesamiento desde UCCE

4300: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Processing from UCCE - [CONNECT] DialogID=46 SendSeqNo=2 Label=4001 TxrHint=false rckey=152070 rcdays=152070 rcseq=0 location= locationpkid= sipheader= uui= whisperAnnounce= callguid=0F46E580000100000000007A0851430A ECC variables=user.media.id: 0F46E580000100000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib: ..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input: complete,user.microapp.UseVXMLParams: N, ECC arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E580000100000000007A085143, Peripheral Variables=

[Connect] publicación en SIP_SS-label 4001

4301: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E580000100000000007A0851430A DialogId=46 [SIP_SWITCH_LEG_DIALOGUE] - Publishing to SIP_SS - [CONNECT] DialogID=46 SendSeqNo=2 Label=4001 TxrHint=false rckey=152070 rcdays=152070 rcseq=0 location= locationpkid= sipheader= uui= whisperAnnounce=

callguid=0F46E58000010000000007A0851430A ECC variables=user.media.id:
0F46E58000010000000007A0851430A,user.microapp.error_code: 0,user.microapp.app_media_lib:
..,user.microapp.media_server: http://192.0.2.11:7000/CVP,user.microapp.caller_input:
complete,user.microapp.UseVXMLParams: N, ECC
arrays=USER_MICROAPP_TOEXTVXML[0]:application=HelloWorld;callid=0F46E58000010000000007A085143,
Peripheral Variables=

Registro de agente de coincidencia de ruta

1968: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} Static route matched 4001 to StaticRoute: patterns like 400> will route to
10.66.75.51
1969: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} Using Local Static Route for sip:4001@10.66.75.51

El LEG VRU se desconecta

4302: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E58000010000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] -
Processing from UCCE - [RELEASE] DialogID=47 SendSeqNo=4 Cause=E_NO_ERROR

[Desconectar] publicar [desconectar]

4303: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID = 0F46E58000010000000007A0851430A, DLGID = 47 [IVR_VRU_LEG_DIALOGUE] -
Publishing [DISCONNECT] DialogID=47 SendSeqNo=4 Cause=E_NO_ERROR, LEGID =
0F46E58000010000000007A0851430A-149438037789633@192.0.2.11, DNIS = 888811111112, ANI = 12345

[Disconnect] publicación en IVR_SS

4304: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_ICM-7-CALL: {Thrd=Event-router-group-0} CALLGUID=0F46E58000010000000007A0851430A DialogId=47 [IVR_VRU_LEG_DIALOGUE] -
Publishing to IVR_SS - [DISCONNECT] DialogID=47 SendSeqNo=4 Cause=E_NO_ERROR

Desconexión VVB

178207: May 02 16:07:56.190 AEST %MIVR-SS_VB-7-UNK: [CALLID=43A31C000001000000000790851430A-149370359030630] Content of POST query:

audium_vxmlLog=

178208: May 02 16:07:56.191 AEST %MIVR-SS_VB-7-UNK:Content of VXML Document:

```
<?xml version="1.0" encoding="UTF-8"?>
```

```
<vxml version="2.0">
```

```
<catch event="vxml.session.error">
```

```
<return event="vxml.session.error" />
```

```
</catch>
```

```
<catch event="telephone.disconnect.hangup">
```

188680: May 02 16:10:49.431 AEST %MIVR-SS_VB-7-UNK: [CALLID=43A31C000001000000000790851430A-149370359030630] traverseDialog: id=Disconnect

196326: May 10 11:21:40.066 AEST %MIVR-JASMIN-7-UNK: [CALLID=0F46E58000010000000007A0851430A-149438037789633] SIP-ltp6-88881111*, State=CONNECTED: setDisconnected processTerminated, cause=NORMAL

Anillo de la pierna trasera

1972: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} Static route matched 91919191 to StaticRoute: patterns like 91919191> will route to 192.0.2.12

1973: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} Using Local Static Route for sip:91919191@192.0.2.12

Invitar a GW VXML

1978: 192.0.2.11: May 10 2017 11:39:50.661 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-149438039066134 - [OUTBOUND]: INVITE TO <sip:91919191@192.0.2.12;transport=tcp> FROM "PSTN PHONE--CVP_11_5_1_0_1_0_344" <sip:12345@192.0.2.11:5060> EXPIRES[10] 100REL[Unsupported]

Sending Message (NB): INVITE sip:91919191@192.0.2.12;transport=tcp SIP/2.0

Via: SIP/2.0/TCP 192.0.2.11:5060;branch=z9hG4bKkIR8MEBv53bzAj6MuGd1vw~~132

Max-Forwards: 67

To: <sip:91919191@192.0.2.12;transport=tcp>

From: "PSTN PHONE--CVP_11_5_1_0_1_0_344" <sip:12345@192.0.2.11:5060>;tag=ds789c1a64

Call-ID: 0F46E580000100000000007A0851430A-149438039066134@192.0.2.11

CSeq: 1 INVITE

Content-Length: 0

Contact: <sip:12345@192.0.2.11:5060;transport=tcp>

Expires: 10

User-Agent: CVP 11.5 (1) ES-1 Build-344

Call-Info: <sip:10.66.74.114:5060>;purpose=x-cisco-origIP

Remote-Party-ID: "PSTN PHONE--CVP_11_5_1_0_1_0_344"

<sip:12345@192.0.2.11>;party=calling;screen=yes;privacy=off

Date: Wed, 10 May 2017 01:17:58 GMT

Min-SE: 1800

Allow: INVITE, OPTIONS, BYE, CANCEL, ACK, PRACK, UPDATE, REFER, SUBSCRIBE, NOTIFY, INFO, REGISTER

Allow-Events: telephone-event

X-Cisco-CCBProbe: id:192.0.2.14;loc:donnielab;trunks:10

Session-Expires: 1800

Cisco-Gucid: 0F46E580000100000000007A0851430A

Supported: timer

Supported: resource-priority

Supported: replaces

Supported: sdp-anat

App-Info: <192.0.2.11:7000:7443>;ringtone=ringback.wav

El tono de recepción de llamada se establece con la persona que llama

2007: 192.0.2.11: May 10 2017 11:39:50.771 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-128-SIP-19468} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-149438039066134 - [RING-OUT]: Notifying that ringtone is established 200 OK with caller.

Invitación a CUCM de la plataforma de agente

2013: 192.0.2.11: May 10 2017 11:39:50.771 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-123-SIP-19464} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-149438039077135 - [OUTBOUND]: INVITE TO <sip:4001@10.66.75.51;transport=tcp> FROM "PSTN PHONE--CVP_11_5_1_0_1_0_344" <sip:12345@192.0.2.11:5060> EXPIRES[60] 100REL[Unsupported]

Llamada conectada

2049: 192.0.2.11: May 10 2017 11:39:58.817 +1000: %CVP_11_5_SIP-7-CALL: {Thrd=pool-1-thread-130-

SIP-19471} CALLGUID = 0F46E580000100000000007A0851430A LEGID = 0F46E580000100000000007A0851430A-149438039077135 - [OUTBOUND]: Acked the invite.

Información Relacionada

- [Soporte Técnico y Documentación - Cisco Systems](#)