

Probleemoplossing voor een C-Series server opnieuw opstarten

Inhoud

[Inleiding](#)

[Voorwaarden](#)

[Gebruikte componenten](#)

[Achtergrondinformatie](#)

[Verwacht herstart](#)

[Onverwachte herstart](#)

[Belangrijkste punten](#)

[Logbundels voor analyse verzamelen](#)

[Verwacht resultaat voor verschillende omstandigheden voor herstart en afsluiten](#)

[Herstart vanuit OS - ESXi, RHEL en Windows](#)

[OBFL-logboek](#)

[RHEL - /var/log/boodschappen](#)

[Windows - Event Meld](#)

[Uitschakelen van OS - ESXi, RHEL en Windows](#)

[OBFL-logboek:](#)

[ESXi - /var/log/hostd.log](#)

[RHEL - /var/log/boodschappen](#)

[Windows - Event Meld](#)

[Ingeschakeld via CIMC](#)

[OBFL-logboek:](#)

[Stroomprogramma van CIMC](#)

[OBFL-logboek](#)

[Uitgeschakeld via CIMC](#)

[OBFL-logboek](#)

[Stroomverlies van PSU-defect](#)

[OBFL-logboek](#)

[Voorkant knop uit](#)

[OBFL-logboek](#)

[Aan/uit](#)

[OBFL-logboek](#)

[Gerelateerde informatie](#)

Inleiding

Dit document beschrijft hoe te bepalen of een herstart of shutdown werd gestart in hardware of van het besturingssysteem.

Er zijn een aantal goede loglocaties om te focussen op wanneer u bepaalt waarom een server is herstart of stopgezet. Wanneer u doorzoekt via de Tech Support (CIMC) van Cisco Integrated

Management Controller (CIMC), bekijkt u de loggen /var/log/messen of Onboard Foutenvastlegging (OBFL).

De voorbeelduitvoer die in dit document wordt geleverd, komt van /var/log/messen of OBFL zowel als OS logbestanden voor ESXi, RHEL en Windows.

Voorwaarden

Er zijn geen specifieke vereisten van toepassing op dit document.

Gebruikte componenten

De informatie in dit document is gebaseerd op de volgende software- en hardware-versies:

- Cisco Unified Computing System (UCS) C200-M1 firmware versie 1.4(3w)
- Cisco UCS C210-M2 firmware versie 1.4(3w)
- Cisco UCS C220-M3 firmware versie 2.0(3d)
- Cisco UCS C220-M4 firmware versie 2.0(3f)
- ESXi 5,0 U2
- RHEL 6.6
- Windows 2008 R2

De informatie in dit document is gebaseerd op de apparaten in een specifieke laboratoriumomgeving. Alle apparaten die in dit document worden beschreven, hadden een opgeschoonde (standaard)configuratie. Als uw netwerk live is, moet u de potentiële impact van elke opdracht begrijpen.

Achtergrondinformatie

De computer kan opnieuw worden opgestart, naar verwachting of onverwacht. Wanneer een herstart wordt verwacht, is het mogelijk dat niet alle belanghebbende partijen dit verwachten. Het is belangrijk om een veranderingscontroleproces in te voeren voor elke herstart- of sluitingstaken om ervoor te zorgen dat iedereen op de hoogte is van de actie.

Verwacht herstart

Dit is elke herstart- of shutdown-gebeurtenis die opzettelijk werd geïnitieerd door een persoon, proces of script. Dit kan op een van verschillende manieren van start gaan. Deze logfragmenten kunnen helpen om te identificeren welk rebootscenario zich voordeed, zodat je kunt achterhalen wie of wat de actie heeft ondernomen:

- Via de CIMC-GUI
- Van het besturingssysteem
- Wanneer u op de voorpaneel knop van de voorkant van de server drukt

Onverwachte herstart

Dit is elke herstart die niet gepland of verwacht wordt, maar die kan nog steeds worden verwacht door de persoon of het proces dat de actie heeft gestart. Mogelijk is er ook een hardwarestoring

opgetreden zoals een PSU-storing of een stroomverlies in het datacenter. Deze kunnen op verschillende manieren van start gaan.

Als wordt bepaald dat de knop op het voorpaneel is ingedrukt, kunt u opsporen wie op het moment van de herstart fysiek toegang tot het datacenter had. Als het om een stroomprobleem gaat, laat het team van het datacenter zien of er op dat moment een stroomstoring was.

- Via de CIMC-GUI
- Van het besturingssysteem
- Wanneer u op de voorpaneel knop van de voorkant van de server drukt
- Door hardwarestoring zoals een PSU-defect of een slechte voedingskabel
- Stroomverdeler (PDU) defect in het datacenter
- UPS-storing of stroomverlies of -uitval bij het datacenter

Belangrijkste punten

- CIMC geïnitieerde reboots, shutdowns, en machtsonen omvatten altijd het "do_power" sleutelwoord in de logbestanden.
- Voorste paneeldruk omvat "passthrough_pin2_isr" wanneer u latere versies van de firmware uitvoert. Ook is er waarschijnlijk geen correlerende gebeurtenis op OS-niveau.
- OS geïnitieerde reboots en shutdowns hebben een geassocieerd OS-niveau gebeurtenis. Let ook op dat "do_power" niet is vastgelegd en dat "High Voltage Mode" in plaats daarvan is vastgelegd.

Logbundels voor analyse verzamelen

Voordat u de relevante stammen bekijkt, moet u eerst de logbundels genereren. Gebruik deze bronnen om de benodigde logbestanden te maken voor referentie wanneer u met de uitvoervoorbeelden in dit document vergelijkt:

C-Series CIMC-technische ondersteuning

[Visuele gids voor het verzamelen van technische ondersteuningsbestanden \(serie B en C\)](#)

ESXi

[vmware - kennisbasis](#)

RHEL

[Wat is een rapport en hoe moet je er een maken in Red Hat Enterprise Linux 4.6 en later?](#)

Windows

[Een Windows Event-logbestand archiveren](#)

Verwacht resultaat voor verschillende omstandigheden voor herstart en afsluiten

Herstart vanuit OS - ESXi, RHEL en Windows

OBFL-logboek

```
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 1
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[readPostData]:525:BIOS_POST_CMPLT Asserted --> BIOS has
completed
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 0
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]:566:
BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:1860:
block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ: HostDescriptor = 4740 : Filename =
BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:BIOSReader:1304: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4740 : FName =
BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:129:[lpc_reset_seen]
LPC Reset Count is Different [0x77:0x78] Asserted LPC Reset Seen
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x83.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x84.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x85.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x86.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x89.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x8a.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x91.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x92.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:200:[transition_function]
Starting Transition to [High Voltage Mode] from [Unknown Mode]
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x83.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x84.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x85.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x86.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x89.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x8a.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x91.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x92.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:220:[transition_function]
Transition to [High Voltage Mode] Success
...
5:2017 Mar 2 09:47:01:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/DimmTempOffset
5:2017 Mar 2 09:47:06:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 1
5:2017 Mar 2 09:47:06:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_usb1_1.c:2290:
USB FS: VDD Power WAKEUP- Power Good = OFF
5:2017 Mar 2 09:47:06:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech.txt
5:2017 Mar 2 09:47:06:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:2561:USB HS: VDD Power = OFF
5:2017 Mar 2 09:47:06:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4756 : FName =
BiosTech.txt
5:2017 Mar 2 09:47:06:BMC:IPMI:1497: Rack_FanCtrl.c:1183:fscUpdateActualFanPolicyFile:
Applied Policy: N/A, Configuration Status: PENDING - Host powered off
5:2017 Mar 2 09:47:06:BMC:IPMI:1466: Pilot2SrvPower.c:466:Blade Power Changed To: [ OFF ]
5:2017 Mar 2 09:47:06:BMC:selparser:1547: selparser.c:710:
# 7E 03 00 00 01 02 00 00 6A 30 B8 58 20 00 04 25 05 00 00 00 08 00 FF FF # 37e | 03/02/2017
09:47:06
| CIMC | Entity presence MAIN_POWER_PRS #0x05 | Device Absent | Asserted
...
```

```

5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:2561:USB HS: VDD Power = ON
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:2685:Failed USB2.0 register
test
5:2017 Mar  2 09:47:12:BMC:kernel:-:last message repeated 2 times
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 0
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]:566:
BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1860:
block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ: HostDescriptor = 4778 : Filename =
BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:BIOSReader:1304: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4778 : FName =
BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:selparser:1547: selparser.c:710:
# 7F 03 00 00 01 02 00 00 6F 30 B8 58 20 00 04 25 05 00 00 00 08 01 FF FF # 37f
| 03/02/2017 09:47:11 | CIMC | Entity presence MAIN_POWER_PRS #0x05 | Device Present | Asserted
5:2017 Mar  2 09:47:12:BMC:IPMI:1495: Pilot2SrvPower.c:466:Blade Power Changed To: [ ON ]

```

Controleer de ESXi logt voor meer informatie over waarom het OS deze gebeurtenis op gang bracht.

- /var/log/vmksuSummary.log
- /var/log/vmkernel.log
- /var/log/hostd.log
- /var/log/shell.log

[VMware KB](#)

RHEL - /var/log/boodschappen

```

May 12 12:55:00 localhost rtkit-daemon[10450]: Demoting known real-time threads.
May 12 12:55:00 localhost rtkit-daemon[10450]: Successfully demoted thread
10987 of process 10987 (/usr/bin/pulseaudio).
May 12 12:55:00 localhost console-kit-daemon[10311]: WARNING: no sender#012
May 12 12:55:00 localhost rtkit-daemon[10450]: Demoted 1 threads.
May 12 12:55:00 localhost rpcbind: rpcbind terminating on signal.
Restart with "rpcbind -w" May 12 12:55:00 localhost init:
Disconnected from system bus
May 12 12:55:00 localhost auditd[3587]: The audit daemon is exiting.
May 12 12:55:00 localhost kernel: type=1305 audit(1431453300.949:33):
audit_pid=0 old=3587 auid=4294967295 ses=4294967295 subj=system_u:
system_r:auditd_t:s0 res=1
May 12 12:55:01 localhost kernel: type=1305 audit(1431453301.053:34):
audit_enabled=0 old=1 auid=4294967295 ses=4294967295 subj=system_u:
system_r:auditctl_t:s0 res=1
May 12 12:55:01 localhost kernel: Kernel logging (proc) stopped.
May 12 12:55:01 localhost rsyslogd: [origin software="rsyslogd" swVersion="5.8.10"
x-pid="3617" x-info="http://www.rsyslog.com"] exiting on signal 15.
May 12 12:58:27 localhost kernel: imklog 5.8.10, log source = /proc/kmsg started.
May 12 12:58:27 localhost rsyslogd: [origin software="rsyslogd" swVersion="5.8.10"
x-pid="3631" x-info="http://www.rsyslog.com"] start
May 12 12:58:27 localhost kernel: Initializing cgroup subsys cpuset
May 12 12:58:27 localhost kernel: Initializing cgroup subsys cpu
May 12 12:58:27 localhost kernel: Linux version 2.6.32-504.el6.x86_64
(mockbuild@x86-023.build.eng.bos.redhat.com) (gcc version 4.4.7 20120313
(Red Hat 4.4.7-11) (GCC) ) #1 SMP Tue Sep 16 01:56:35 EDT 2014
May 12 12:58:27 localhost kernel: Command line:
ro root=/dev/mapper/VolGroup-lv_root rd_NO_LUKS LANG=en_US.UTF-8

```

```
rd_NO_MD rd_LVM_LV=VolGroup/lv_swap SYSFONT=latacyrheb-sun16 crashkernel=auto
rd_LVM_LV=VolGroup/lv_root KEYBOARDTYPE=pc KEYTABLE=us rd_NO_DM rhgb quiet
```

Voor meer tips over het opnieuw opstarten van RHEL-oplossingen, zie dit [Red Hat KBArticle](#).

Windows - Event Meld

Event 1074

The process **Explorer.EXE has initiated the restart** of computer WIN-5JPBKNNMRRNF on behalf of user WIN-5JPBKNNMRRNF\Administrator for the following reason: Other (Planned)
Reason Code: 0x85000000
Shutdown Type: restart
Comment: C-Series Test

Event 1074

The **process C:\Windows\system32\winlogon.exe (WIN-5JPBKNNMRRNF) has initiated the restart** of computer WIN-5JPBKNNMRRNF on behalf of user WIN-5JPBKNNMRRNF\Administrator for the following reason: No title for this reason could be found
Reason Code: 0x500ff
Shutdown Type: restart Comment:

Event 109

The kernel power manager has initiated a shutdown transition.

Event 13

The operating system is shutting down at system time ?2015?-?05?-?18T08:26:32.778837300Z.

Event 12

The operating system started at system time ?2015?-?05?-?18T08:28:28.610798500Z.

Voor meer tips op Windows Event Logs van Windows, raadpleeg dit [TechNet-artikel](#).

Uitschakelen van OS - ESXi, RHEL en Windows

OBFL-logboek:

```
5:2015 May 12 18:03:37:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs
Fn:0x6 Cmd:0x6 Data&colon; 0x85 0x83
5:2015 May 12 18:03:37:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 18:03:38:BMC:kernel:--<5>[lpc_reset_isr_handler]:79:LPC
Reset ISR -> ResetState: 1
5:2015 May 12 18:03:38:BMC:kernel:--<5>[readPostData]:519:BIOS_POST_
CMPLT Asserted --> BIOS has completed
5:2015 May 12 18:03:38:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS:
VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 18:03:38:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 12 18:03:38:BMC:IPMI:1563: Pilot3SrvPower.c:484:Blade Power Changed To: [ OFF ]
5:2015 May 12 18:03:38:BMC:video_trigger:--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015May 12 18:03:39:BMC:selparser:1602: selparser.c:678:
# 11 04 00 00 01 02 00 00 7A 40 52 55 2C 60 04 DC 1A 00 00 00 F4 03 00 00
# 411 | 05/12/2015 18:03:38 | Unknown #0x602c | Unknown #0x1a |
```

5:2015 May 12 18:03:39:BMC:selparser:1602: selparser.c:678:
12 04 00 00 01 02 00 00 7A 40 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF # 412 |
05/12/2015 18:03:38 | CIMC | Entity presence MAIN_POWER_PRS #0xa9 | Device Absent | Asserted

ESXi - /var/log/hostd.log

2015-05-15T00:46:01.809Z [28B69B90 info 'TaskManager'] Task Created :
haTask--vim.host.AutoStartManager.autoPowerOff-245137084
2015-05-15T00:46:01.810Z [28AE7B90 info 'TaskManager'] Task Completed :
haTask--vim.host.AutoStartManager.autoPowerOff-245137084 Status success
2015-05-15T00:46:01.814Z [28AE7B90 verbose 'Default']
CloseSession called for session id=526869fe-3f96-f54a-4bb6-41250fa3242b
2015-05-15T00:46:01.814Z [28AE7B90 info 'ha-eventmgr'] Event 107 : User dcui logged out
2015-05-15T00:46:01.822Z [28AA6B90 verbose 'Proxysvc Req00060'] New proxy client SSL
(TCP(local=127.0.0.1:0, peer=127.0.0.1:58274))
2015-05-15T00:46:01.822Z [28AA6B90 warning 'Proxysvc Req00060'] Error reading from
client while waiting for header: N7Vmacore15SystemExceptionE(Connection reset by peer)
2015-05-15T00:46:02.077Z [29441B90 verbose 'Proxysvc Req00061'] New proxy client
SSL(TCP(local=127.0.0.1:443, peer=127.0.0.1:58877))
2015-05-15T00:46:02.088Z [28AE7B90 verbose 'Ticket 52 27 9e 4d f0 16 ac aa-13 f8
86 f9 f1 a3 61 8b'] Ticket issued for dcui
2015-05-15T00:46:02.090Z [2930AB90 verbose 'Ticket 52 27 9e 4d f0 16 ac aa-13 f8
86 f9 f1 a3 61 8b'] Ticket used
Accepted password for user dcui from 127.0.0.1
2015-05-15T00:46:02.090Z [2930AB90 info '**Vimsvc**'] **[Auth]: User dcui**
2015-05-15T00:46:02.091Z [2930AB90 info 'ha-eventmgr'] Event 108 :
User dcui@127.0.0.1 logged in
2015-05-15T00:46:02.093Z [29366B90 info 'InternalServiceInstance'] **Shutting down service**
2015-05-15T00:46:22.104Z [FFAB2AD0 error 'Default'] SSLStreamImpl::
BIORead (291a1000) timed out
Section for VMware ESX, pid=2882, version=5.0.0, build=build-914586, option=Release

RHEL - /var/log/boodschappen

May 12 13:03:24 localhost init: tty (/dev/tty2) main process
(10152) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty3) main process
(10154) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty4) main process
(10156) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty5) main process
(10158) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty6) main process
(10162) killed by TERM signal
May 12 13:03:25 localhost abrttd: Got signal 15, exiting
May 12 13:03:29 localhost acpid: exiting
May 12 13:03:30 localhost NetworkManager[9732]: <info>
caught signal 15, shutting down normally.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth0): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth0): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth1): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth1): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth4): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth4): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth5): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth5): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth6): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth6): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth7): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth7): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth2): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth2): taking down device.

```
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth3): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth3): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> exiting (success)
May 12 13:03:31 localhost rpcbind: rpcbind terminating on signal.
Restart with "rpcbind -w"
May 12 13:03:31 localhost rtkit-daemon[10367]: Demoting known real-time threads.
May 12 13:03:31 localhost rtkit-daemon[10367]: Successfully demoted thread 1
0365 of process 10365 (/usr/bin/pulseaudio).
May 12 13:03:31 localhost rtkit-daemon[10367]: Demoted 1 threads.
May 12 13:03:31 localhost console-kit-daemon[10228]: WARNING: no sender#012
May 12 13:03:31 localhost init: Disconnected from system bus
May 12 13:03:31 localhost auditd[3601]: The audit daemon is exiting.
May 12 13:03:31 localhost kernel: type=1305 audit(1431453811.355:22):
audit_pid=0 old=3601 auid=4294967295 ses=4294967295 subj=system_u
:system_r:auditd_t:s0 res=1
May 12 13:03:31 localhost kernel: type=1305 audit(1431453811.459:23):
audit_enabled=0 old=1 auid=4294967295 ses=4294967295 subj=system_u
:system_r:auditctl_t:s0 res=1
May 12 13:03:31 localhost kernel: Kernel logging (proc) stopped.
May 12 13:03:31 localhost rsyslogd: [origin software="rsyslogd"
swVersion="5.8.10" x-pid="3631" x-info="http://www.rsyslog.com"] exiting on signal 15.
```

Windows - Event Meld

Event 1074

The process C:\Windows\system32\winlogon.exe (WIN-5JPBKNMMRNF)
has initiated the power off of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator
for the following reason: No title for this reason could be found
Reason Code: 0x500ff
Shutdown Type: power off
Comment

Event 1074

The **process Explorer.EXE has initiated the shutdown** of computer
WIN-5JPBKNMMRNF on behalf of
user WIN-5JPBKNMMRNF\Administrator for the following reason: Other (Planned)
Reason Code: 0x85000000
Shutdown Type: shutdown
Comment: Shut down Test

Event 109

The kernel power manager has initiated a shutdown transition.

Event 13

The operating system is shutting down at system time ?2015?-?05?-?18T08:38:13.237425300Z.

Ingeschakeld via CIMC

OBFL-logboek:

```
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[__do_power_on]:340:__do_power_on
5:2015 May 12 18:08:31:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0 Cmd:0x2
Data&colon; 0x1
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[__do_power_on]:345:Power Driver:
Power On Logic Pulse for 250ms @ 25164275955:2015 May 12 18:08:31:BMC:IPMI:
1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 18:08:31:BMC:AUDIT:20723: Server power state modify (op:power-on)
```



```

5:2015 May 12 18:08:31:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/
se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 18:08:31:BMC:IPMI:1565: Pilot3SrvPower.c:481: ->
Power State On: LPC RESET is NOT IN RESET; powerOnLPCOff[2]
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]
:2685:Failed USB2.0 register test
5:2015 May 12 18:08:31:BMC:IPMI:1565: Pilot3SrvPower.c:484:Blade
Power Changed To: [ ON ]
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 0
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 12 18:08:31:BMC:IPMI:1566: Pilot3SrvPower.c:191:Pilot2SrvPowerOn
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[__do_power_on]:375:
Power Driver: Power On Logic Done @ 2516427846
5:2015 May 12 18:08:31:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:BIOSReader:1247: BIOSReader.c:748:File Close
: /var/nuova/BIOS/BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1406 : Filename = BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1406 : FName = BiosTech_7.txt
5:2015 May 12 18:08:32:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1408 : Filename = BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:748:File Close
: /var/nuova/BIOS/BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1408 : FName = BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:video_trigger:-: video_trigger.c:262:Sending
event_ipmi_power_state_change (ON) ..
5:2015 May 12 18:08:32:BMC:video_trigger:-: video_trigger.c:137:Sending
event_server_boot_start..
5:2015 May 12 18:08:32:BMC:video_trigger:-: video_trigger.c:148:
Will be able to send event_server_crash..
5:2015 May 12 18:08:32:BMC:selparser:1602: selparser.c:678:
# 13 04 00 00 01 02 00 00 A0 41 52 55 2C 60 04 DC 1A 00 00 00 74 07 00 00
# 413 | 05/12/2015 18:08:32 | Unknown
#0x602c | Unknown #0x1a |
5:2015 May 12 18:08:32:BMC:selparser:1602: selparser.c:678:
# 14 04 00 00 01 02 00 00 A0 41 52 55 20 00 04 25 00 00 00 00 08 00 FF FF
# 414 | 05/12/2015 18:08:32 | CIMC | Entity presence BIOS_POST_CMPLT
#0x00 | Device Absent | Asserted
5:2015 May 12 18:08:32:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1410 : Filename = BiosTech_5.txt
5:2015 May 12 18:08:32:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1410 : FName = BiosTech_5.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_5.txt

```

Stroomprogramma van CIMC

5:2015 May 12 19:18:45:BMC:kernel:-:<5>[do_cycle]:560:do_cycle
5:2015 May 12 19:18:45:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0
Cmd:0x2 Data:0x2
5:2015 May 12 19:18:45:BMC:kernel:-:<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 19:18:45:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 19:18:45:BMC:kernel:-:<5>[__do_power_off]:300:Power Driver:
Power Off Logic @ 2520641182
5:2015 May 12 19:18:45:BMC:IPMI:1566: **Pilot3SrvPower.c:539:**
Pilot2SrvPowerCycle
5:2015 May 12 19:18:45:BMC:AUDIT:20723: **Server power state modify**
(op:power-cycle)
5:2015 May 12 19:18:49:BMC:kernel:-:<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 12 19:18:49:BMC:kernel:-:<5>[readPostData]:519:
BIOS_POST_CMPLT Asserted --> BIOS has completed
5:2015 May 12 19:18:49:BMC:kernel:-:<5>drivers/bmc/usb/
usb1.1/se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 19:18:49:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 12 19:18:49:BMC:video_trigger:-: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 12 19:18:49:BMC:IPMI:1532: **Pilot3SrvPower.c:484:**
Blade Power Changed To: [OFF]
5:2015 May 12 19:18:49:BMC:selparser:1602: selparser.c:678:
1A 04 00 00 01 02 00 00 19 52 52 55 20 00 04 25 A9 00 00 08 00 FF FF
41a | 05/12/2015 19:18:49 | CIMC | Entity presence MAIN_POWER_PRS #0xa9
| Device Absent | Asserted
5:2015 May 12 19:18:55:BMC:selparser:1602: selparser.c:678:
1B 04 00 00 01 02 00 00 1E 52 52 55 2C 60 04 DC 1A 00 00 00 74 03 00 00
41b | 05/12/2015 19:18:54 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 19:18:55:BMC:selparser:1602: selparser.c:678:
1C 04 00 00 01 02 00 00 1E 52 52 55 2C 60 04 16 16 00 00 00 0A 00 00 00
41c | 05/12/2015 19:18:54 | Unknown
#0x602c | Microcontroller/Coprocessor
#0x16 | Transition to Running | Asserted
5:2015 May 12 19:19:05:BMC:kernel:-:<5>[__do_power_on]:340:__do_power_on
5:2015 May 12 19:19:05:BMC:kernel:-:<5>[__do_power_on]:345:
Power Driver: Power On Logic Pulsefor 250ms @ 2520661694
5:2015 May 12 19:19:05:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/
se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 12 19:19:05:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 12 19:19:05:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 19:19:05:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 12 19:19:05:BMC:kernel:-:<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 0
5:2015 May 12 19:19:05:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 12 19:19:05:BMC:IPMI:1566: **Pilot3SrvPower.c:542:Pilot2SrvPowerCycle**
5:2015 May 12 19:19:05:BMC:kernel:-:<5>[__do_power_on]
:375:Power Driver: Power On Logic Done @ 2520661945
5:2015 May 12 19:19:05:BMC:IPMI:1566: **Pilot3SrvPower.c:481:**
-> Power State On: LPC RESET is NOT IN RESET; powerOnLPCOff[2]
5:2015 May 12 19:19:05:BMC:IPMI:1566: **Pilot3SrvPower.c:484:**
Blade Power Changed To: [ON]
5:2015 May 12 19:19:06:BMC:BIOSReader:1247: BIOSReader.c:242:
File Open : BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:kernel:-:<5>[block_transfer_fetch_host_

```
request_for_app]:1860:block_transfer_fetch_host_request_for_app:
BT_OPEN_FOR_READ: HostDescriptor = 1466 : Filename = BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block_transfer_fetch_host_
request_for_app]:1944:block_transfer_fetch_host_request_for_app :
BT_FILE_CLOSE : HostBTDescr = 1466 : FName = BiosTech_7.txt
5:2015 May 12 19:19:06:BMC:selparser:1602: selparser.c:678:
# 1D 04 00 00 01 02 00 00 29 52 52 55 2C 60 04 DC 1A 00 00 00 74 07 00 00
# 41d | 05/12/2015 19:19:05 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (ON) ..
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:137:
Sending event_server_boot_start ..
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:148:
Will be able to send event_server_crash ..
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block_transfer_fetch_host_
request_for_app]:1860:block_transfer_fetch_host_request_for_app:
BT_OPEN_FOR_READ: HostDescriptor = 1468 : Filename = BiosTech_6.txt
```

Uitgeschakeld via CIMC

OBFL-logboek

```
5:2015 May 12 20:18:25:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 20:18:25:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0
Cmd:0x2 Data&colon; 0x0
5:2015 May 12 20:18:25:BMC:kernel:--<5>[__do_power_off]:300:Power Driver:
Power Off Logic@ 2524221543
5:2015 May 12 20:18:25:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 20:18:25:BMC:AUDIT:20723: Server power state modify (op:power-off)
5:2015 May 12 20:18:30:BMC:kernel:--<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 12 20:18:30:BMC:kernel:--<5>[readPostData]:519:BIOS_POST_CMPLT
Asserted --> BIOS has completed
5:2015 May 12 20:18:30:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 20:18:30:BMC:IPMI:1567: Pilot3SrvPower.c:484:Blade Power Changed To: [ OFF ]
5:2015 May 12 20:18:30:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 12 20:18:30:BMC:selparser:1602: selparser.c:678:
# 24 04 00 00 01 02 00 00 16 60 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 424 | 05/12/2015 20:18:30 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
5:2015 May 12 20:18:30:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 12 20:18:31:BMC:vkcs_mux:1582: vkcs_mux.c:76:[REQ] 00 01
5:2015 May 12 20:18:36:BMC:IPMI:1566: Pilot3SrvPower.c:348:Pilot2SrvPowerOff
5:2015 May 12 20:18:37:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 20:18:37:BMC:blade-power:11311: host-power.c:53:POWER Off
5:2015 May 12 20:18:38:BMC:run-update:11313: ../..
/src/runupdate.c:511:Run-update Process Starting.
5:2015 May 12 20:18:38:BMC:run-update:11313: ../..
/src/runupdate.c:44:Setting FP Button Lock: current state 0
5:2015 May 12 20:18:38:BMC:kernel:--<5>[lock_front_panel_buttons]
:1373:Front Panel Power Button is now permanently locked.
5:2015 May 12 20:18:38:BMC:kernel:--<5>[lock_front_panel_buttons]
:1378:Front Panel Reset Button is now permanently locked.
```

Stroomverlies van PSU-defect

OBFL-logboek

```

5:2015 May 15 14:29:12:BMC:kernel:-:<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 15 14:29:12:BMC:kernel:-:<5>[readPostData]:519:
BIOS_POST_CMPLT Asserted --> BIOS has completed
5:2015 May 15 14:29:12:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/
se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:29:12:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 15 14:29:12:BMC:IPMI:1532: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 15 14:29:12:BMC:video_trigger:-: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 33 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 08 27 00 00 03 00 FF FF
# 433 | 05/15/2015 14:29:12 | CIMC | Power supply PSU1_AC_OK
#0x27 | State Deasserted | Asserted
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 34 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 08 42 00 00 04 01 FF FF
# 434 | 05/15/2015 14:29:12 | CIMC | Power supply PMBUS_ALERT #0x42
| Predictive Failure asserted | Asserted
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 35 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 435 | 05/15/2015 14:29:12 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
5:1970 Jan 1 00:02:48:BMC:kernel:-:<5>Linux version 2.6.35.10
(buildsa@savbu-swbmc-vb1) (gcc version 3.4.5)
#2 Tue Nov 18 07:09:13 PST 2014 Unversioned directory
4:1970 Jan 1 00:02:48:BMC:kernel:-:<4>CPU: ARM926EJ-S [41069265]
revision 5 (ARMv5TEJ), cr=00053177
4:1970 Jan 1 00:02:48:BMC:kernel:-:<4>CPU: VIVT data cache, VIVT instruction cache
4:1970 Jan 1 00:02:48:BMC:kernel:-:<4>Machine: ServerEngines PILOT3 Hornet Board
4:1970 Jan 1 00:02:48:BMC:kernel:-:<4>Memory policy: ECC disabled, Data cache writeback

```

Voorkant knop uit

OBFL-logboek

```

5:2015 May 15 14:50:19:BMC:kernel:-:<5>[passthrough_pin2_isr]:158:x86
Host Power Button Press
5:2015 May 15 14:50:19:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 15 14:50:19:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:2561:
USB HS: VDD Power = ON
5:2015 May 15 14:50:31:BMC:IPMI:1561: Bridge.c:1478:audit from:kcs Fn:0x6
Cmd:0x6 Data&colon; 0x85 0x83
5:2015 May 15 14:50:31:BMC:IPMI:1561: Bridge.c:1484:audit Resp:0x0
5:2015 May 15 14:50:35:BMC:kernel:-:<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 1
5:2015 May 15 14:50:35:BMC:kernel:-:<5>[readPostData]:519:BIOS_POST_CMPLT
Asserted --> BIOS has completed
5:2015 May 15 14:50:35:BMC:video_trigger:-: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 15 14:50:35:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:50:35:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 15 14:50:35:BMC:IPMI:1531: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 15 14:50:35:BMC:selparser:1602: selparser.c:678:
# A2 04 00 00 01 02 00 00 BB 07 56 55 2C 60 04 DC 1A 00 00 00 F4 03 00 00

```

```
# 4a2 | 05/15/2015 14:50:35 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 15 14:50:35:BMC:selparser:1602: selparser.c:678:
# A3 04 00 00 01 02 00 00 BB 07 56 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 4a3 | 05/15/2015 14:50:35 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
```

Aan/uit

OBFL-logboek

```
5:2015 May 15 14:51:18:BMC:kernel:-:<5>[passthrough_pin2_isr]
:158:x86 Host Power Button Press
5:2015 May 15 14:51:18:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/se_pilot2
_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:51:18:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 15 14:51:19:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/se_pilot2_
_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 0
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 15 14:51:19:BMC:IPMI:1561: Pilot3SrvPower.c:481: ->
Power State On: LPC RESET is NOT IN RESET; powerOnLPCoff[0]
5:2015 May 15 14:51:19:BMC:IPMI:1561: Pilot3SrvPower.c:484:
Blade Power Changed To: [ ON ]
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_6.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 118 : Filename = BiosTech_7.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_5.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 119 : Filename = BiosTech_6.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 120 : Filename = BiosTech_5.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 121 : Filename = BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 121 : FName = BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:video_trigger:-: video_trigger.c:262:
Sending event_ipmi_power_state_change (ON) ..
5:2015 May 15 14:51:19:BMC:video_trigger:-: video_trigger.c:137:
Sending event_server_boot_start ..
5:2015 May 15 14:51:19:BMC:video_trigger:-: video_trigger.c:148
:Will be able to send event_server_crash ..
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 123 : Filename = BiosTech_3.txt
```

```
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_3.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 123 : FName = BiosTech_3.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_3.txt
```

Gerelateerde informatie

- [C-Series probleemoplossing voor herstart](#)
- [Technische ondersteuning en documentatie – Cisco Systems](#)