

# ASR 5000系列如何在初始觸發後確定警報的當前故障率

## 目錄

[問題](#)

[答案](#)

[相關思科支援社群討論](#)

## 問題

如何在初始觸發後的任何時間確定警報的當前故障率。要找到初始故障率可能更為明顯，但是，是否有可能在幾小時後找到當前的故障率？

## 答案

當初始SNMP陷阱、日誌和警報跟蹤受監控閾值的初始故障率時，如何獲取當前故障率可能不明顯。在「show threshold」的底部，該命令報告與上一輪詢問隔內當前失敗率相關的所有警報的狀態。

```
[local]PDSN> show threshold
Friday June 12 04:39:32 UTC 2015
```

Outstanding alarms:

```
Threshold Name:    aaa-acct-failure-rate
Alarm Source:      System
Last Measured: 77% Raise Time: 2015-Jun-11+22:15:05
```

```
[local]PDSN> show thresh
Friday June 12 05:34:04 UTC 2015
```

Outstanding alarms:

```
Threshold Name:    aaa-acct-failure-rate
Alarm Source: System Last Measured: 65%
Raise Time:        2015-Jun-11+22:15:05
```

```
[local]PDSN> show thresh
Friday June 12 06:06:07 UTC 2015
```

Outstanding alarms:

```
Threshold Name:    aaa-acct-failure-rate
Alarm Source:      System
Last Measured: 61%
Raise Time:        2015-Jun-11+22:15:05
```

```
[local]PDSN> show alarm outstanding verbose
Friday June 12 04:41:28 UTC 2015
```

```
Severity Object          Timestamp                Alarm ID
```

-----  
Alarm Details  
-----

Minor Chassis Thursday **June 11 22:15:05** U 5770524519230406656  
<28:aaa-acct-failure-rate> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

2015-Jun-11+22:15:05.418 [alarmctrl 65201 info] [8/0/5185 <evlogd:0> alarmctrl.c:192] [software internal system critical-info syslog] **Alarm condition:** id 5015057a08690000 (Minor): <28:aaa-acct-failure-rate> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

Thu Jun 11 **22:15:05** 2015 Internal trap notification 222 (**ThreshAAAacctFailRate**) threshold 25% measured value 32%

2015-Jun-12+07:15:05.210 [alarmctrl 65200 info] [8/0/5185 <evlogd:0> alarmctrl.c:285] [software internal system critical-info syslog] **Alarm cleared:** id 5015057a08690000: <28:aaa-acct-failure-rate> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

Fri Jun 12 07:15:05 2015 Internal trap notification 223 (**ThreshClearAAAacctFailRate**) threshold 20%**measured value 0%**

[local]PDSN> show threshold Friday June 12 13:45:26 UTC 2015

...

No outstanding alarm